

ws2022_exam_r

Student Group

First Name	Surname	Matrikel Nr.


Table of Contents

Exercise E1 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	2
Exercise E1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	5
Exercise E2 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	6
Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)	6
Exercise E3 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	9
Exercise E4 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	9
Exercise E5 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022)	10
Exercise E6 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)	11

Exercise E1 Equivalent linear Source
(written test, approx. 14 % of a 60-minute written test, WS2022)

The circuit in the following has to be simplified.
 Result

$$\begin{aligned} U_{\text{S}} &= U_{\text{AB}} = 4.5 \text{ V} \\ R_{\text{i}} &= R_{\text{AB}} = 6 \Omega \end{aligned}$$




Calculated the internal resistance R_{i} and the source voltage U_{S} of an equivalent linear voltage source on the connectors A and B .
 $R_1=5.0 \Omega$, $U_2=6.0 \text{ V}$, $R_3= 10 \Omega$, $I_4=4.2 \text{ A}$, $R_5=10 \Omega$, $R_6=7.5 \Omega$, $R_7=15 \Omega$ Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :
$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4$$
 The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:
$$U_{24} = I_{24} \cdot R_{135}$$

$$U_{AB} = U_{24} \cdot \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} = (U_2 \cdot \frac{R_1}{R_1 + R_4}) \cdot \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5}$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

Therefore the voltage between A and B is given as:

$$U_{AB} = U_{24} \cdot \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} = (U_2 \cdot \frac{R_1}{R_1 + R_4}) \cdot \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5}$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($=0 \Omega$, so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$:

$$U_{AB} = \frac{6.0 \text{ V}}{5.0 \Omega} - 4.2 \Omega \cdot \frac{15 \Omega \cdot 2.5 \Omega}{7.5 \Omega + 15 \Omega + 2.5 \Omega} || R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

Exercise E1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)

2. A refrigerator is explained with the effect of resistance on the refrigeration system. The circuit has a resistance of 15Ω and a voltage of 6 V . Your answer:

Its temperature coefficients are: $\alpha = 0.01 \text{ K}^{-1}$ and $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$

Result
The temperature inside the refrigeration system can reach down to $-40 \text{ }^\circ\text{C}$.

$$R = 6.5 \text{ } \Omega \text{ at } -40 \text{ }^\circ\text{C}$$

The power of the resistor is $P = U^2 / R$ and $Q = P \cdot t$. Therefore, a solution is to use a heat pump.

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2) \quad | \quad \Delta T = T_{\text{end}} - T_{\text{start}}$$

$$R = 10 \text{ } \Omega \cdot (1 + 0.01 \text{ K}^{-1} \cdot (-40 \text{ }^\circ\text{C} - 25 \text{ }^\circ\text{C}) + 71 \cdot 10^{-6} \text{ K}^{-2} \cdot (-40 \text{ }^\circ\text{C} - 25 \text{ }^\circ\text{C})^2)$$

Exercise E2 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the complex impedance Z of the circuit shown in the figure through the components. R and X_L shall be given.

After analysis, the full bridge circuit can be simplified to a series circuit in phasor domain. $Z = (2 + j) \Omega + (4 - j) \Omega + 5 \Omega$

Solution
.. Calculate the physical values of the two components.
Solution $R = 0.2 \Omega$ $X_L = 4.68 \Omega$

Solution
$$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \text{ V}}{(2 + j) \Omega + (4 - j) \Omega + 5 \Omega} = \frac{50 \text{ V}}{11 \Omega}$$

The voltage of the AC source is $u(t) = 50 \text{ V} \cdot \sin(2\pi \cdot 300 \text{ Hz} \cdot t)$
resulting in $\underline{U} = 50 \text{ V} \cdot e^{j(2\pi \cdot 300 \text{ Hz} \cdot t)}$
Therefore, the component 4.68Ω is a pure inductor with $\underline{Z} = j4.68 \Omega$
impedance. $\underline{X}_L = j4.68 \Omega$
$$\underline{Z} = (2 + j) \Omega + (4 - j) \Omega + 5 \Omega = 11 \Omega$$

The phase φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{0}{11}\right) = 0^\circ$
With the complex part $\underline{Z} = 11 \Omega$ and $\underline{U} = 50 \text{ V}$
$$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \text{ V}}{11 \Omega} = 4.545 \text{ A}$$

The phase φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{I})}{\text{Re}(\underline{I})}\right) = \arctan\left(\frac{0}{4.545}\right) = 0^\circ$

Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)


2. Calculate the complex impedance Z of the circuit shown in the figure. The AC source is $u(t) = 3.0 \text{ V} \cdot \sin(2\pi \cdot 15 \text{ kHz} \cdot t)$. The circuit consists of an inductor of $330 \mu\text{H}$ and a capacitor of $0.22 \mu\text{F}$, all in series.

Solution
Result
.. Draw the circuit diagram of the bridge circuit.

Calculate the complex impedance Z of the circuit shown in the figure. The AC source is $u(t) = 3.0 \text{ V} \cdot \sin(2\pi \cdot 15 \text{ kHz} \cdot t)$. The circuit consists of an inductor of $330 \mu\text{H}$ and a capacitor of $0.22 \mu\text{F}$, all in series.
Solution
Result
$$\underline{Z} = j\omega L - \frac{1}{j\omega C} = j(2\pi \cdot 15 \text{ kHz} \cdot 330 \mu\text{H}) - \frac{1}{j(2\pi \cdot 15 \text{ kHz} \cdot 0.22 \mu\text{F})}$$

$$\underline{Z} = j3.96 \Omega - j1.59 \Omega = j2.37 \Omega$$

The phase φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{2.37}{0}\right) = 90^\circ$



Exercise E3 Impedances at different Frequencies
(written test, approx. 18 % of a 60-minute written test, WS2022)

2. A series circuit consists of a resistor with a resistance of $R_1 = 1.00 \text{ k}\Omega$, a capacitor with a capacitance of $C_1 = 40 \text{ nF}$, and an inductor with an inductance of $L_1 = 4.7 \text{ }\mu\text{H}$. The circuit is connected to an AC voltage source with a voltage of $U = 10 \text{ V}$ and a frequency of $f = 4 \text{ MHz}$. Calculate the absolute value of the impedance $|Z|$ of the circuit.

Solution

$|Z| = \sqrt{R^2 + (X_L - X_C)^2}$

$|Z| = \sqrt{(1.00 \text{ k}\Omega)^2 + (2\pi \cdot 4 \text{ MHz} \cdot 4.7 \text{ }\mu\text{H} - \frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}})^2}$

$|Z| = \sqrt{(1.00 \text{ k}\Omega)^2 + (117.6 \text{ }\Omega - 994.7 \text{ }\Omega)^2}$

$|Z| = \sqrt{(1.00 \text{ k}\Omega)^2 + (-877.1 \text{ }\Omega)^2}$

$|Z| = \sqrt{(1.00 \text{ k}\Omega)^2 + 769.3 \text{ k}\Omega^2}$

$|Z| = \sqrt{1.00 \text{ k}\Omega^2 + 769.3 \text{ k}\Omega^2}$

$|Z| = \sqrt{770.3 \text{ k}\Omega^2}$

$|Z| = 27.75 \text{ k}\Omega$

Exercise E4 Resistance of a Wire by Resistivity
(written test, approx. 6 % of a 60-minute written test, WS2022)

2. For heating elements used to heat the oven in a domestic use electric oven, a power dissipation (= heat flow) of $P = 40 \text{ W}$ is necessary. Calculate the current I needed to operate the heating elements.

The Nichrome wire has a resistivity of $\rho = 1.10 \cdot 10^{-6} \text{ }\Omega \cdot \text{m}$.

The heating element is $l = 3 \text{ m}$ long and has a diameter of $d = 3.57 \text{ mm}$.

Calculate the resistance R of the heating element.

Solution

$P = U \cdot I = R \cdot I^2 \rightarrow I = \sqrt{\frac{P}{R}}$

$$\sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \cdot \Omega}} \quad \text{align*}$$

$$\begin{aligned} R &= \rho \cdot l \cdot \frac{1}{A} \quad \& \quad | \quad \text{with } A = r^2 \cdot \pi = \\ &= \frac{1}{4} d^2 \cdot \pi \quad \& \quad R = \rho \cdot l \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ &= 1.10 \cdot 10^{-6} \cdot \Omega \cdot \text{m} \cdot \frac{4 \cdot 3 \cdot \text{m}}{(3.57 \cdot 10^{-3} \cdot \text{m})^2 \cdot \pi} \quad \& \quad \end{aligned}$$


Exercise E5 Charging Capacitors
(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (with the light bulb) is a series of R_1 and R_2 and a capacitor C as circled in Figure 5.2.2.2. The voltage across the capacitor is again 0 V at the moment $t_0 = 0 \text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2 = 1 \text{ ms}$ after closing the switch.

Solution To solve this, first create an equivalent linear voltage source from U , R_1 , and R_2 .

The ideal voltage source U is in series with R_1 and R_2 . The voltage u_c is independent of this series $(U - I \cdot R_1)^2$.

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting R_2 .




The circuit contains a voltage source $U = 12 \text{ V}$, a switch S_1 , a resistor of $R_1 = 20 \Omega$ and a capacitor of $C = 100 \mu\text{F}$.

The switch S_2 to an additional consumer R_2 will be considered to be open for the first tasks. At the moment $t_0 = 0 \text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0) = 0 \text{ V}$.

.. First do not consider the light bulb - it is not connected to the RC circuit.

Calculate the point of time t_1 when $u_c(t_1) = 0.5 \cdot U$.

Solution



An equivalent linear voltage source can be given with U_s , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$ The internal resistance is given by substituting the ideal voltage source with its resistance ($R = 0 \Omega$, short-circuit).


$$R_i = R_1 \parallel R_B = 10 \Omega$$

$$u_c(t) = U_s \cdot (1 - e^{-t/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-t/(10 \Omega \cdot 100 \mu F)})$$

The following formula describes the time course of $u_c(t)$ which has to be $u_c(t_1) = 0.5 \cdot U$:

$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to t :

$$(1 - e^{-t/\tau}) = 0.5 \implies e^{-t/\tau} = 0.5 \implies -t/\tau = \ln(0.5) \implies t = \tau \cdot \ln(0.5) \implies t = R_1 \cdot C \cdot \ln(0.5)$$




Exercise E6 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be solved at $U = 200 \text{ V}$. Calculate R_{eq} between A and B and the current I through R_B .

Solution

$$R_{eq} = 132.8 \Omega$$

Now a wye-delta transformation is necessary.




Since $R_2=R_3$ and based on the equations for the transformation, the transformed R_Y is given as:
$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \Omega)^2}{3 \cdot 100 \Omega} = \frac{1}{3} \cdot 100 \Omega = 33.33 \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:
$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \Omega + (33.33 \Omega + 400 \Omega) \parallel (33.33 \Omega + 100 \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \sim \Omega + 200 \sim \Omega + 200 \sim \Omega) \parallel (100 \sim \Omega + 100 \sim \Omega) \parallel R_{\text{eq}} = \{ \{ 500 \sim \Omega \cdot 200 \sim \Omega \} \over { 500 \sim \Omega + 200 \sim \Omega } \} \parallel$$

From:

<https://mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

https://mexle.te.hs-heilbronn.de/ee1/ws2022_exam_r

Last update: **2023/03/31 12:10**

