

task_pdkggtyexxy1ktu3_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E6 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) 2

complex impedance, exam ee1 WS2022

Exercise E6 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)

Exercise E6: A series circuit consists of a resistor \$R_1\$ with \$R_1 = 10 \text{ }\Omega\$, a capacitor \$C_1\$ with \$C_1 = 40 \text{ nF}\$, and an inductor \$L_1\$ with \$L_1 = 4.7 \text{ }\mu\text{H}\$. The circuit is connected to an AC voltage source \$u(t) = 60 \sin(2\pi \cdot 450 \text{ kHz} \cdot t) \text{ V}\$. Determine the absolute value of the impedance \$|Z|\$ of the circuit at \$f = 4 \text{ MHz}\$.

Solution

$|Z| = 10.0 \text{ }\Omega$

A series circuit means that the current is constant on every component. The equivalent impedance for \$R\$ and \$L\$ combined is given by $Z = R + j\omega L$. The equivalent impedance for \$C\$ is given by $Z = -j/\omega C$. The total impedance is $Z = R + j\omega L - j/\omega C$. The absolute value of the impedance is $|Z| = \sqrt{R^2 + (\omega L - 1/\omega C)^2}$. At \$f = 4 \text{ MHz}\$, $\omega = 2\pi \cdot 4 \cdot 10^6 \text{ rad/s}$. $|Z| = \sqrt{10^2 + (2\pi \cdot 4 \cdot 10^6 \cdot 4.7 \cdot 10^{-6} - 1/(2\pi \cdot 4 \cdot 10^6 \cdot 40 \cdot 10^{-9}))^2} = 10.0 \text{ }\Omega$.

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: https://mexle.te.hs-heilbronn.de/electrical_engineering_and_electronics/task_pdkggyexxy1ktu3_with_calculation

Last update: 2023/04/02 00:27

