

task_wjttvmydrskzhcim_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Component Parameters (written test, approx. 10 % of a 120-minute written test, SS2021)	2
--	---

complex voltage divider, RMS, inductor, exam ee2 SS2021

Exercise E1 Component Parameters

(written test, approx. 10 % of a 120-minute written test, SS2021)

Determine the component parameters of an electric motor presents a resistive inductive load! For the next exercises consider the following: The RMS values of the series resistance R_{M} and the inductance L_{M} are to be determined below. Both results in the impedance of the motor.

This resulted in the recorded current of

a) Derive in general the equation for the absolute value of the impedance of the motor.

$$|Z| = \sqrt{(2\pi \cdot f \cdot L_{\text{M}})^2 + R_{\text{M}}^2}$$

$$R_{\text{M}} = 4 \cdot B \cdot \Omega$$

$$L_{\text{M}} = 100 \cdot \text{mH}; I_1 = 5 \cdot \text{A}$$

$$L_{\text{M}} = 100 \cdot \text{mH}; I_2 = 5 \cdot \text{mA}$$

b) Since we have the absolute values of the impedances from the specified formulas from a) and b) this has the advantage that R_{M} will cancel out:

$$Z_2^2 - Z_1^2 = (2\pi \cdot f_2 \cdot L_{\text{M}})^2 + R_{\text{M}}^2 - \left((2\pi \cdot f_1 \cdot L_{\text{M}})^2 + R_{\text{M}}^2 \right)$$

$$\underline{Z_2^2 - Z_1^2 = (2\pi \cdot f_2 \cdot L_{\text{M}})^2 - (2\pi \cdot f_1 \cdot L_{\text{M}})^2}$$

The complex impedance \underline{Z} for a resistive inductive load R_{M} and L_{M} in series circuit is given as

$$\underline{Z} = R_{\text{M}} + j \cdot X_{\text{L}}$$

$$\underline{Z} = R_{\text{M}} + j \cdot (2\pi \cdot f \cdot L_{\text{M}})$$

$$\underline{Z} = R_{\text{M}} + j \cdot (2\pi \cdot f \cdot L_{\text{M}})$$

$$\underline{Z} = R_{\text{M}} + j \cdot (2\pi \cdot f \cdot L_{\text{M}})$$

$$\underline{Z} = R_{\text{M}} + j \cdot (2\pi \cdot f \cdot L_{\text{M}})$$

$$\underline{Z} = R_{\text{M}} + j \cdot (2\pi \cdot f \cdot L_{\text{M}})$$

$$\underline{Z} = R_{\text{M}} + j \cdot (2\pi \cdot f \cdot L_{\text{M}})$$

$$\underline{Z} = R_{\text{M}} + j \cdot (2\pi \cdot f \cdot L_{\text{M}})$$

And then to L_{M} :

$$L_{\text{M}} = \frac{1}{2\pi} \sqrt{\frac{Z_2^2 - Z_1^2}{f_2^2 - f_1^2}}$$

With the values:

$$L_{\text{M}} = \frac{1}{2\pi} \sqrt{\frac{(10 \cdot \Omega)^2 - (6.25 \cdot \Omega)^2}{(100 \cdot \text{s}^{-1})^2 - (50 \cdot \text{s}^{-1})^2}} = 14.346 \cdot \text{mH}$$

The resistance value R_{M} can be derived from

$$R_{\text{M}} = \sqrt{(10 \cdot \Omega)^2 - (2\pi \cdot 100 \cdot \text{s}^{-1} \cdot 0.014346 \cdot \text{H})^2} = 4.3301 \cdot \Omega$$

From:

<https://mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

https://mexle.te.hs-heilbronn.de/ee2/task_wjttvmydrskzhcim_with_calculation?rev=1720050503

Last update: **2024/07/04 01:48**

