

task_pdkggtyexxy1ktu3_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) 2

complex impedance, exam ee1 WS2022

Exercise E1 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)

Exercise E1: A series circuit consists of a resistor R1 = 1.00 Ω, an inductor L = 4.7 μH, and a capacitor C = 40 nF. The circuit is connected to an AC voltage source with a peak-to-peak voltage of 10 V and a frequency of 450 kHz. Calculate the magnitude of the total impedance Z_T and the current I_T through the circuit.

Solution

$$R_1 = 1.00 \Omega$$

$$R_2 = 10.0 \Omega$$

A series circuit means that the current is constant on every component.

The equivalent impedance for R and L combined is given by

Parallel circuit means that the voltage is the same on R2 and C2

$$Z_{parallel} = \frac{R_2 \cdot X_{C2}}{R_2 + X_{C2}}$$

Since X_{C2} is perpendicular to R_2 , this can be simplified to $Z_{parallel} = \frac{R_2 \cdot X_{C2}}{\sqrt{R_2^2 + X_{C2}^2}}$

$$Z_{parallel} = \frac{10 \cdot (-j40)}{\sqrt{10^2 + (-40)^2}} = \frac{-j400}{\sqrt{1700}} = -j12.1 \Omega$$

Therefore, the resulting current of the parallel circuit is given as:

$$I_{parallel} = \frac{U}{Z_{parallel}} = \frac{10}{-j12.1} = j0.826 \text{ A}$$

Back to the first formula:

$$Z_T = R_1 + j\omega L + Z_{parallel} = 1.00 + j2.7 + (-j12.1) = 1.00 - j9.4 \Omega$$

$$|Z_T| = \sqrt{1.00^2 + 9.4^2} = 9.42 \Omega$$

$$I_T = \frac{U}{|Z_T|} = \frac{10}{9.42} = 1.06 \text{ A}$$

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: https://mexle.te.hs-heilbronn.de/electrical_engineering_1/task_pdkggyexxy1ktu3_with_calculation?rev=1680388047

Last update: 2023/04/02 00:27

