

Exam Winter Semester 2022

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Resistivity and temperature dependent Resistance (written test, approx. 7 % of a 60-minute written test, SS2023)	2
Exercise E4 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	3
Exercise E1 Resistivity and temperature dependent Resistance (written test, approx. 7 % of a 60-minute written test, SS2023)	3
Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	4

**Exercise E1 Resistivity and temperature dependent Resistance
(written test, approx. 7 % of a 60-minute written test, SS2023)**

The conductivity of a dielectric material is described by the Arrhenius law: $\sigma = \sigma_0 \exp(-E_a/kT)$ with $\sigma_0 = 10^{17} \text{ s}^{-1} \text{ m}^{-1} \text{ V}^{-1}$ and $E_a = 0.8 \text{ eV}$. The resistivity of the dielectric material is $\rho(20 \text{ }^\circ\text{C}) = 10^{17} \text{ } \Omega \text{ m}$.
 The resistivity of the dielectric material is $\rho(20 \text{ }^\circ\text{C}) = 10^{17} \text{ } \Omega \text{ m}$.
 The resistivity of the dielectric material is $\rho(20 \text{ }^\circ\text{C}) = 10^{17} \text{ } \Omega \text{ m}$.

Solution
 The resistivity of the dielectric material is $\rho(20 \text{ }^\circ\text{C}) = 10^{17} \text{ } \Omega \text{ m}$.

For the given material the temperature coefficients in the range $20 \text{ }^\circ\text{C}$ and $55 \text{ }^\circ\text{C}$

$$\begin{aligned} R(55 \text{ }^\circ\text{C}) &= R(20 \text{ }^\circ\text{C}) \cdot (1 + \alpha \cdot \Delta T + \beta \cdot T^2 + \dots) \\ &= 80 \text{ } \Omega \cdot (1 - 0.048 \text{ } \text{K}^{-1} \cdot (35 \text{ }^\circ\text{C} - 20 \text{ }^\circ\text{C}) + 0.00057 \text{ } \text{K}^{-2} \cdot (35 \text{ }^\circ\text{C} - 20 \text{ }^\circ\text{C})^2) \end{aligned}$$

Calculate the resistance for the dielectric material for $20 \text{ }^\circ\text{C}$.

Solution

$$\begin{aligned} R(20 \text{ }^\circ\text{C}) &= \rho \cdot \frac{d}{A} \\ &= 10^{17} \text{ } \Omega \text{ m} \end{aligned}$$

$$I = \frac{U}{R} = \frac{0.8 \cdot 10^{-6} \cdot 1.80}{1.10 \cdot 10^{-6}} \approx 1.36 \text{ A}$$

resistivity, power, exam ee1 ss2023

Exercise E4 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

A heating element made of nichrome wire with a temperature coefficient of \$1.80 \cdot 10^{-5} \text{ K}^{-1}\$ is used. The electric power dissipation (= heat flow) of \$P=40 \text{ W}\$ is necessary. Calculate the current \$I\$ and the operating voltage \$U\$ for heating elements. The Nichrome wire has a resistivity of \$1.10 \cdot 10^{-6} \text{ } \Omega \cdot \text{m}\$.

The heating element is \$3 \text{ m}\$ long and has a diameter of \$3.57 \text{ mm}\$.
 Solution: Calculate the resistance \$R\$ of the heating element.

Solution

$$P = U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \approx 11.0 \text{ A}$$

$$R = \rho \cdot \frac{l}{A} \quad | \quad A = r^2 \cdot \pi = \frac{1}{4} d^2 \cdot \pi \quad | \quad R = \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} = 1.10 \cdot 10^{-6} \text{ } \Omega \cdot \text{m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \approx 0.33 \text{ } \Omega$$

resistivity, power, exam ee1 ws2022

Exercise E1 Resistivity and temperature dependent Resistance (written test, approx. 7 % of a 60-minute written test, SS2023)

The conductivity \$\sigma\$ of a dielectric material is described by the Arrhenius law: \$\sigma = \sigma_0 \cdot \exp(-E_a / (k_B \cdot T))\$. For \$E_a = 0.8 \text{ eV}\$, \$\sigma_0 = 10^{17} \text{ S/m}\$, and \$k_B = 8.617 \cdot 10^{-5} \text{ eV/K}\$, calculate the conductivity \$\sigma\$ at \$T = 300 \text{ K}\$ and \$T = 400 \text{ K}\$.

Solution

The resistivity of the dielectric material is \$\rho(T) = 1/\sigma(T) = 10^{-17} \text{ } \Omega \cdot \text{m} \cdot \exp(E_a / (k_B \cdot T))\$.

For the given material the temperature coefficients in the range \$20 \text{ } ^\circ\text{C} \le T \le 55 \text{ } ^\circ\text{C}\$ are given as \$\alpha = -0.048 \text{ K}^{-1}\$ and \$\beta = +0.00057 \text{ K}^{-2}\$.

$$\rho(55 \text{ } ^\circ\text{C}) = \rho(20 \text{ } ^\circ\text{C}) \cdot (1 + \alpha \cdot \Delta T + \beta \cdot T^2 + \dots) = 80 \text{ G}\Omega \cdot (1 - 0.048 \text{ K}^{-1} \cdot (35 \text{ K}) + 0.00057 \text{ K}^{-2} \cdot (35 \text{ K})^2)$$

Calculate the resistance for the dielectric material for $20 \text{ }^\circ\text{C}$.

Solution

$$R(20 \text{ }^\circ\text{C}) = \rho \cdot \frac{d}{A} = 10^{17} \frac{\Omega \cdot \text{m}}{1 \text{ m}^2} \cdot \{0.8 \cdot 10^{-6} \text{ m}\}$$

[resistivity, power, exam ee1 ss2023](#)

**Exercise E1 Resistance of a Wire by Resistivity
(written test, approx. 6 % of a 60-minute written test, WS2022)**

Result

A minimum power dissipation (= heat flow) of $P=40 \text{ W}$ is necessary.
 Calculate the minimum resistance R of the heating element.
 The Nichrome wire has a resistivity of $1.10 \cdot 10^{-6} \text{ } \Omega \text{ m}$.
 The heating element is 3 m long and has a diameter of 3.57 mm .
 1. Calculate the resistance R of the heating element.

```

Solution
\begin{align*} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \\ &= \sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{align*}

\begin{align*} R &= \rho \cdot \frac{l}{A} \quad | \quad \text{with } A = r^2 \cdot \pi = \\ &= \frac{1}{4} d^2 \cdot \pi \quad || \quad R = \rho \cdot \frac{l}{\frac{1}{4} d^2 \cdot \pi} \quad || \quad R = \\ &= 1.10 \cdot 10^{-6} \text{ } \Omega \text{ m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \quad || \quad \end{align*}
  
```

resistivity, power, exam ee1 ws2022

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: https://mexle.te.hs-heilbronn.de/electrical_engineering_1/ws2022_exam?rev=1676152918

Last update: 2023/02/11 23:01

