

Exam Winter Semester 2022

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022) 3

Exercise E1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) 6

Exercise E2 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022) 7

Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022) 7

Exercise E3 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) 10

Exercise E4 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) 10

Exercise E5 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022) 11

Exercise E6 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022) 12

Exercise E3 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022) 14

Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) 18

Exercise E5 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022) 19

Exercise E7 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022) 19

Exercise E6 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) 22

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) 22


Exercise E4 Charging Capacitors (written test, approx. 16 % of a 60-minute written test,

WS2022) 23
Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute
written test, WS2022) 24

**Exercise E1 Equivalent linear Source
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.
Result

$$\begin{aligned} U_{\text{rs}} &= U_{\text{AB}} = 4.5 \text{ V} \\ R_{\text{i}} &= R_{\text{AB}} = 6 \Omega \end{aligned}$$




Calculated the internal resistance R_{i} and the source voltage U_{rs} of an equivalent linear voltage source on the connectors A and B .
 $R_1=5.0 \Omega$, $U_2=6.0 \text{ V}$, $R_3= 10 \Omega$, $I_4=4.2 \text{ A}$, $R_5=10 \Omega$, $R_6=7.5 \Omega$, $R_7=15 \Omega$
 Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :
$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4$$
 The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:
$$U_{24}$$

$$U_{AB} = U_{24} \cdot \left(\frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - I_4 \cdot R_1 || R_3 || R_5$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

Therefore the voltage between A and B is given as:

$$U_{AB} = U_{24} \cdot \left(\frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - \left(\frac{U_2}{R_1} - I_4 \right) \cdot \left(R_1 || R_3 || R_5 \right)$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($=0 \Omega$, so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$:

$$U_{AB} = \left(\frac{6.0 \text{ V}}{5.0 \Omega} \right) - 4.2 \text{ A} \cdot \left(\frac{15 \Omega \cdot 2.5 \Omega}{7.5 \Omega + 15 \Omega + 2.5 \Omega} \right)$$

$$R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

Exercise E1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)

2. A refrigerator is explained with the effect of resistance on refrigeration system. The circuit has a resistance of 15Ω and a voltage of 6 V at 25°C for your answer.

Its temperature coefficients are: $\alpha = 0.01 \text{ K}^{-1}$ and $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$

Result The temperature inside the refrigeration system can reach down to -40°C .

$$R_0 = 15 \Omega$$

The power of the resistor is $P = U \cdot I$ and $Q = P \cdot t$. Therefore, a solution is to increase the resistance of the resistor to reduce the heat flow.

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

$$\Delta T = T_{\text{end}} - T_{\text{start}}$$

$$R = 15 \Omega \cdot \left(1 + 0.01 \text{ K}^{-1} \cdot (-40^\circ \text{C} - 25^\circ \text{C}) + 71 \cdot 10^{-6} \text{ K}^{-2} \cdot (-40^\circ \text{C} - 25^\circ \text{C})^2 \right)$$

Exercise E2 Analyzing complex Impedances
 (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the complex power \underline{S} in a circuit with $\underline{U} = 100 \angle 0^\circ$ V and $\underline{Z} = 10 + j10 \Omega$. The real and imaginary components (P and Q) shall be given.

After analysis, the full complex power \underline{S} can be calculated as $\underline{S} = \underline{U} \cdot \underline{I}^*$. The real power P is the real part of \underline{S} and the reactive power Q is the imaginary part of \underline{S} .

Solution

$$\underline{S} = \underline{U} \cdot \underline{I}^* = 100 \angle 0^\circ \cdot \frac{100 \angle 0^\circ}{10 + j10} = 1000 \frac{1 \angle 0^\circ}{\sqrt{2} \angle 45^\circ} = 707.1 \angle -45^\circ \text{ VA}$$

Solution

$$P = 707.1 \cos(-45^\circ) = 500 \text{ W}$$

$$Q = 707.1 \sin(-45^\circ) = -500 \text{ var}$$

The voltage $\underline{U} = 100 \angle 0^\circ$ V and the impedance $\underline{Z} = 10 + j10 \Omega$ are given. The resulting current $\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{100 \angle 0^\circ}{10 + j10} = 7.07 \angle -45^\circ$ A.

Therefore, the complex power $\underline{S} = \underline{U} \cdot \underline{I}^* = 100 \angle 0^\circ \cdot 7.07 \angle 45^\circ = 707.1 \angle -45^\circ$ VA. The real power $P = 707.1 \cos(-45^\circ) = 500$ W and the reactive power $Q = 707.1 \sin(-45^\circ) = -500$ var.

With the complex power $\underline{S} = 500 - j500$ VA, the real power $P = 500$ W and the reactive power $Q = -500$ var can be calculated as $P = \text{Re}\{\underline{S}\}$ and $Q = \text{Im}\{\underline{S}\}$.

The phase φ can be calculated as $\varphi = \arctan\left(\frac{Q}{P}\right) = \arctan\left(\frac{-500}{500}\right) = -45^\circ$.

Exercise E1 Complex Impedance Circuit
 (written test, approx. 15 % of a 60-minute written test, WS2022)

2. Calculate the complex power \underline{S} in a circuit with $\underline{U} = 100 \angle 0^\circ$ V and $\underline{Z} = 10 + j10 \Omega$. The real and imaginary components (P and Q) shall be given.

After analysis, the full complex power \underline{S} can be calculated as $\underline{S} = \underline{U} \cdot \underline{I}^*$. The real power P is the real part of \underline{S} and the reactive power Q is the imaginary part of \underline{S} .

Solution

$$\underline{S} = \underline{U} \cdot \underline{I}^* = 100 \angle 0^\circ \cdot \frac{100 \angle 0^\circ}{10 + j10} = 1000 \frac{1 \angle 0^\circ}{\sqrt{2} \angle 45^\circ} = 707.1 \angle -45^\circ \text{ VA}$$


Solution

$$P = 707.1 \cos(-45^\circ) = 500 \text{ W}$$

$$Q = 707.1 \sin(-45^\circ) = -500 \text{ var}$$

The voltage $\underline{U} = 100 \angle 0^\circ$ V and the impedance $\underline{Z} = 10 + j10 \Omega$ are given. The resulting current $\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{100 \angle 0^\circ}{10 + j10} = 7.07 \angle -45^\circ$ A.

Therefore, the complex power $\underline{S} = \underline{U} \cdot \underline{I}^* = 100 \angle 0^\circ \cdot 7.07 \angle 45^\circ = 707.1 \angle -45^\circ$ VA. The real power $P = 707.1 \cos(-45^\circ) = 500$ W and the reactive power $Q = 707.1 \sin(-45^\circ) = -500$ var.



Exercise E3 Impedances at different Frequencies
(written test, approx. 18 % of a 60-minute written test, WS2022)

2. A series circuit consists of a resistor with a resistance of $R_1 = 1.00 \text{ k}\Omega$ and a capacitor with a capacitance of $C_1 = 40 \text{ nF}$. The voltage across the resistor is $U_{R_1} = 100 \text{ V}$. Calculate the absolute value of the impedance of the circuit at $f = 4 \text{ MHz}$.

Solution

$$R_1 = 1.00 \text{ k}\Omega$$

$$R_2 = 10.0 \text{ k}\Omega$$

A series circuit means that the current is constant on every component.

The equivalent impedance for R_1 and R_2 combined is given by
$$R_{\text{series}} = R_1 + R_2 = 1.00 \text{ k}\Omega + 10.0 \text{ k}\Omega = 11.0 \text{ k}\Omega$$

Parallel circuit means that the voltage is the same on R_3 and C_3
$$\frac{1}{X_{\text{parallel}}} = \frac{1}{R_3} + \frac{1}{X_{C_3}}$$

Since X_{C_3} is perpendicular to R_3 , this can be simplified to
$$X_{\text{parallel}} = \frac{R_3 \cdot X_{C_3}}{\sqrt{R_3^2 + X_{C_3}^2}}$$

R_3 is perpendicular to X_{C_3} (It has to, since R_3 is perpendicular to X_{L_2} and X_{C_3} is perpendicular to X_{L_2})
$$X_{\text{parallel}}^2 = \frac{R_3^2 \cdot X_{C_3}^2}{R_3^2 + X_{C_3}^2}$$

Therefore, the resulting current of the parallel circuit is given as:
$$I_{\text{parallel}} = I_{R_3} + I_{C_3}$$

This can be rearranged to
$$I_{\text{parallel}} = \frac{U_{R_3}}{R_3} + \frac{U_{R_3}}{X_{\text{parallel}}}$$

$$I_{\text{parallel}} = \frac{100 \text{ V}}{11.0 \text{ k}\Omega} + \frac{100 \text{ V}}{\frac{10.0 \text{ k}\Omega \cdot 40 \text{ nF} \cdot (2\pi \cdot 4 \text{ MHz})^2}{10.0 \text{ k}\Omega^2 + (40 \text{ nF} \cdot 2\pi \cdot 4 \text{ MHz})^2}}$$

Back to the first formula:
$$R_3 \cdot I_{\text{parallel}} = X_{\text{parallel}} \cdot I_{\text{parallel}}$$

$$\frac{100 \text{ V}}{11.0 \text{ k}\Omega} = \frac{X_{\text{parallel}} \cdot I_{\text{parallel}}}{11.0 \text{ k}\Omega}$$

Exercise E4 Resistance of a Wire by Resistivity
(written test, approx. 6 % of a 60-minute written test, WS2022)

2. For heating elements used to heat the oven at a temperature of $180 \text{ }^\circ\text{C}$, an electric power dissipation (= heat flow) of $P = 40 \text{ W}$ is necessary. Calculate the current I needed to operate the heating elements.

The Nichrome wire has a resistivity of $\rho = 1.10 \cdot 10^{-6} \text{ }\Omega \cdot \text{m}$.

The heating element is $l = 3 \text{ m}$ long and has a diameter of $d = 3.57 \text{ mm}$.

Solution

Calculate the resistance R of the heating element.

$$P = U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}}$$

$$\sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \cdot \Omega}} \quad \text{align*}$$

$$\begin{aligned} R &= \rho \cdot l \cdot \frac{1}{A} \quad \& \quad | \quad \text{with } A = r^2 \cdot \pi = \\ &= \frac{1}{4} \cdot d^2 \cdot \pi \quad \& \quad R = \rho \cdot l \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ &= 1.10 \cdot 10^{-6} \cdot \Omega \cdot \text{m} \cdot \frac{4 \cdot 3 \cdot \text{m}}{(3.57 \cdot 10^{-3} \cdot \text{m})^2 \cdot \pi} \quad \& \quad \end{aligned}$$


Exercise E5 Charging Capacitors
(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (with the light bulb) is a series of R_1 and R_2 and a capacitor C and a switch S_1 and a switch S_2 . The voltage across the capacitor is again 0 V at the moment $t_0 = 0 \text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2 = 1 \text{ ms}$ after closing the switch.

Solution: To solve this, first create an equivalent linear voltage source from U , R_1 , and R_2 .

The ideal voltage source U is in series with R_1 and R_2 . The voltage u_c is independent of this series.

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting S_1 .




The circuit contains a voltage source $U = 12 \text{ V}$, a switch S_1 , a resistor of $R_1 = 20 \Omega$ and a capacitor of $C = 100 \mu\text{F}$.

The switch S_2 to an additional consumer R_2 will be considered to be open for the first tasks. At the moment $t_0 = 0 \text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0) = 0 \text{ V}$.

.. First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time t_1 when $u_c(t_1) = 0.5 \cdot U$.

Solution



An equivalent linear voltage source can be given with U_s , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$ The internal resistance is given by substituting the ideal voltage source with its resistance ($R_1 = 0 \Omega$, short-circuit).

$$R_i = R_1 \parallel R_B = 10 \Omega$$

$$u_c(t) = U_s \cdot (1 - e^{-t/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-t/(10 \cdot 100 \mu F)})$$

The following formula describes the time course of $u_c(t)$ which has to be $u_c(t_1) = 0.5 \cdot U$:

$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to $(1 - e^{-t/\tau}) = 0.5 \implies e^{-t/\tau} = 0.5 \implies t/\tau = \ln(0.5) \implies t = \tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$



Exercise E6 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be solved at 0V and $R_1 = R_2 = R_3 = 10 \Omega$ and the switch is closed. R_B is given.

Solution

$$R_{\text{eq}} = 132.8 \Omega$$

Now a wye-delta transformation is necessary.




Since $R_2=R_3$ and based on the equations for the transformation, the transformed R_Y is given as:
$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \Omega)^2}{3 \cdot 100 \Omega} = \frac{1}{3} \cdot 100 \Omega = 33.33 \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:
$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \Omega + (33.33 \Omega + 400 \Omega) \parallel (33.33 \Omega + 100 \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \Omega + 200 \Omega + 200 \Omega) \parallel (100 \Omega + 100 \Omega) \parallel R_{\text{eq}} = (500 \Omega) \parallel (200 \Omega) \parallel R_{\text{eq}} = \frac{500 \Omega \cdot 200 \Omega}{500 \Omega + 200 \Omega} \parallel R_{\text{eq}}$$

**Exercise E3 Equivalent linear Source
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.
Result

$$U_{\text{s}} = U_{\text{AB}} = 4.5 \text{ V} \quad R_{\text{i}} = R_{\text{AB}} = 6 \Omega$$




Calculated the internal resistance R_{int} and the source voltage U_{oc} of an equivalent linear voltage source on the connectors A and B . $R_1=5.0 \text{ }\Omega$, $U_2=6.0 \text{ V}$, $R_3= 10 \text{ }\Omega$, $I_4=4.2 \text{ A}$, $R_5=10 \text{ }\Omega$, $R_6=7.5 \text{ }\Omega$, $R_7=15 \text{ }\Omega$ Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4$$

The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:

$$U_{24} = I_{24} \cdot R_{135} + I_{24} \cdot R_2 + I_{24} \cdot R_3 + I_{24} \cdot R_4 + I_{24} \cdot R_5$$

$$U_{AB} = U_{24} \cdot \left(\frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - I_4 \cdot R_1 || R_3 || R_5$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

Therefore the voltage between A and B is given as:

$$U_{AB} = U_{24} \cdot \left(\frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - \left(\frac{U_2}{R_1} - I_4 \right) \cdot \left(\frac{R_7 \cdot R_1 || R_3 || R_5}{R_6 + R_7 + R_1 || R_3 || R_5} \right)$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($=0 \Omega$, so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$:

$$U_{AB} = \left(\frac{6.0 \text{ V}}{5.0 \Omega} - 4.2 \text{ A} \right) \cdot \left(\frac{15 \Omega \cdot 2.5 \Omega}{7.5 \Omega + 15 \Omega + 2.5 \Omega} \right)$$

$$R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)

2. A refrigerator is explained with the effect of resistance on the refrigeration system. The circuit has a resistance of 15Ω and a voltage of 6 V . Your answer:

Its temperature coefficients are: $\alpha = 0.01 \text{ K}^{-1}$ and $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$

Result
The temperature inside the refrigeration system can reach down to $-40 \text{ }^\circ\text{C}$.

$$R = 6.5 \text{ } \Omega \text{ at } -40 \text{ }^\circ\text{C}$$

The power of the resistor is $P = U \cdot I$ and $Q = P \cdot t$. Therefore, a solution is to use a heat pump.

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

$$\text{with } \Delta T = T_{\text{end}} - T_{\text{start}} \implies R = 10 \text{ } \Omega \cdot \left(1 + 0.01 \text{ K}^{-1} \cdot (-40 \text{ }^\circ\text{C} - 25 \text{ }^\circ\text{C}) + 71 \cdot 10^{-6} \text{ K}^{-2} \cdot (-40 \text{ }^\circ\text{C} - 25 \text{ }^\circ\text{C})^2 \right)$$

Exercise E5 Analyzing complex Impedances
 (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the complex power \underline{S} (W and var) of the load \underline{Z} through the components. (\underline{S} and \underline{X}_L) shall be given.

After analysis, the full load impedance \underline{Z} can be extracted and legitimated in phasor notation $\underline{Z} = |Z| \cdot e^{j\varphi}$ with $\varphi = \varphi(\underline{Z}) = \varphi(\underline{U}) - \varphi(\underline{I})$.

Solution
 .. Calculate the physical values of the load components.
 Solution $\underline{R} = 10 \Omega$ and $\underline{X}_L = 20 \Omega$

Solution

$$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \angle 0^\circ}{10 + j20} = 2 \angle -63.4^\circ \text{ A}$$
 The voltage \underline{U} is $50 \angle 0^\circ$ V. The impedance \underline{Z} is $10 + j20 \Omega$.
 The resulting power $\underline{S} = \underline{U} \cdot \underline{I}^* = 50 \angle 0^\circ \cdot 2 \angle 63.4^\circ = 100 \angle 63.4^\circ \text{ VA}$
 The real power $P = 100 \cos(63.4^\circ) = 45 \text{ W}$
 The reactive power $Q = 100 \sin(63.4^\circ) = 90 \text{ var}$
 The phase $\varphi = 63.4^\circ$
 With the complex part $\underline{Z} = 10 + j20 \Omega$ and $\underline{U} = 50 \angle 0^\circ$ V, the current $\underline{I} = 2 \angle -63.4^\circ$ A.
 The phase φ can be calculated as $\varphi = \arctan\left(\frac{-4.68}{0.24}\right) = -10.8^\circ$

Exercise E7 Complex Impedance Circuit
 (written test, approx. 15 % of a 60-minute written test, WS2022)

2. Calculate the current \underline{I} through the load \underline{Z} in the circuit. $\underline{Z} = 10 + j20 \Omega$ and $\underline{U} = 50 \angle 0^\circ$ V.
 The voltage source $u(t) = 3.0 \cdot \sin(2\pi \cdot 15 \cdot t)$ V.
 The circuit consists of a voltage source $u(t)$, an inductor $L = 330 \mu\text{H}$, and a capacitor $C = 0.22 \mu\text{F}$, all in series.

Solution
 Result
 .. Draw the circuit diagram of the given circuit.

Solution


$$\underline{Z} = 10 + j20 \Omega$$

$$\underline{Z}_C = \frac{1}{j\omega C} = \frac{1}{j \cdot 2\pi \cdot 15 \cdot 0.22 \cdot 10^{-6}} = -j15.5 \text{ k}\Omega$$

$$\underline{Z}_L = j\omega L = j \cdot 2\pi \cdot 15 \cdot 330 \cdot 10^{-6} = 31.5 \text{ m}\Omega$$

$$\underline{Z} = 10 + j20 - j15.5 + j0.0315 \approx 10 + j4.5 \text{ k}\Omega$$

$$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{3 \angle 0^\circ}{10 + j4.5} = 0.27 \angle -24.4^\circ \text{ A}$$



Exercise E6 Impedances at different Frequencies
(written test, approx. 18 % of a 60-minute written test, WS2022)

2. A series circuit consists of a resistor with a resistance of $R_1 = 1.00 \text{ k}\Omega$ and a capacitor with a capacitance of $C_1 = 40 \text{ nF}$. The circuit is connected to an AC voltage source with a voltage of $U = 10 \text{ V}$ and a frequency of $f = 4 \text{ MHz}$. Calculate the absolute value of the impedance $|Z|$ of the circuit.

Solution

$$|Z| = \sqrt{R_1^2 + X_{C1}^2}$$

$$|Z| = \sqrt{(1.00 \text{ k}\Omega)^2 + \left(\frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}}\right)^2}$$

A series circuit means that the current is constant on every component.
 The equivalent impedance for R and X_C combined is given by $|Z| = \sqrt{R^2 + X_C^2}$
 Parallel circuit means that the voltage is the same on R_1 and C_1 $\frac{1}{Z} = \frac{1}{R_1} + \frac{1}{X_{C1}}$
 $\frac{1}{Z} = \frac{1}{1.00 \text{ k}\Omega} + \frac{1}{\frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}}}$
 $Z = \frac{1}{\frac{1}{1.00 \text{ k}\Omega} + \frac{1}{\frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}}}}$
 $Z = \frac{1.00 \text{ k}\Omega \cdot \frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}}}{1.00 \text{ k}\Omega + \frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}}}$
 $Z = \frac{1.00 \text{ k}\Omega \cdot 3.98 \text{ }\mu\Omega}{1.00 \text{ k}\Omega + 3.98 \text{ }\mu\Omega}$
 $Z \approx 3.98 \text{ }\mu\Omega$
 Therefore, the resulting current of the parallel circuit is given as:

$$I = \frac{U}{|Z|} = \frac{10 \text{ V}}{3.98 \text{ }\mu\Omega} \approx 2.51 \text{ mA}$$

Exercise E1 Resistance of a Wire by Resistivity
(written test, approx. 6 % of a 60-minute written test, WS2022)

2. For a heating element used to heat the oven at a temperature of $180 \text{ }^\circ\text{C}$, an electric power dissipation (= heat flow) of $P = 40 \text{ W}$ is necessary.
 Calculate the current I needed to operate the heating elements.
 The Nichrome wire has a resistivity of $\rho = 1.10 \cdot 10^{-6} \text{ }\Omega \cdot \text{m}$.

The heating element is $l = 3 \text{ m}$ long and has a diameter of $d = 3.57 \text{ mm}$.
 Calculate the resistance R of the heating element.

Solution

$$P = U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}}$$

$$\sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \cdot \Omega}} \quad \text{align*}$$

$$\begin{aligned} R &= \rho \cdot l \cdot \frac{1}{A} \quad \& \quad | \quad \text{with } A = r^2 \cdot \pi = \\ &= \frac{1}{4} \cdot d^2 \cdot \pi \quad \& \quad R = \rho \cdot l \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ &= 1.10 \cdot 10^{-6} \cdot \Omega \cdot \text{m} \cdot \frac{4 \cdot 3 \cdot \text{m}}{(3.57 \cdot 10^{-3} \cdot \text{m})^2 \cdot \pi} \quad \& \quad \end{aligned}$$


Exercise E4 Charging Capacitors
(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (with the light bulb) is a series of R_1 and R_2 and a capacitor C and a switch S_1 and a switch S_2 . The voltage across the capacitor is again 0 V at the moment $t_0 = 0 \text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2 = 1 \text{ ms}$ after closing the switch.

Solution: To solve this, first create an equivalent linear voltage source from U , R_1 , and R_2 .

The ideal voltage source U is in series with R_1 and R_2 . The voltage u_c is independent of the choice of R_1 and R_2 .

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting S_1 .




The circuit contains a voltage source $U = 12 \text{ V}$, a switch S_1 , a resistor of $R_1 = 20 \text{ }\Omega$ and a capacitor of $C = 100 \text{ }\mu\text{F}$.

The switch S_2 to an additional consumer R_2 will be considered to be open for the first tasks. At the moment $t_0 = 0 \text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0) = 0 \text{ V}$.

.. First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time t_1 when $u_c(t_1) = 0.5 \cdot U$.

Solution



An equivalent linear voltage source can be given with U_s , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$ The internal resistance is given by substituting the ideal voltage source with its resistance ($R_1 = 0 \Omega$, short-circuit).

$$R_i = R_1 \parallel R_B = 10 \Omega$$

$$u_c(t) = U_s \cdot (1 - e^{-t/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-t/(10 \cdot 100 \mu F)})$$

The following formula describes the time course of $u_c(t)$ which has to be $u_c(t_1) = 0.5 \cdot U$:

$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to $(1 - e^{-t/\tau}) = 0.5 \implies e^{-t/\tau} = 0.5 \implies t/\tau = \ln(0.5) \implies t = \tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$




Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be solved at once, $R_1 = R_2 = R_3 = 10 \Omega$ and the voltage $U = 10V$ is given. R_B .

Solution

$$R_{\text{eq}} = 132.8 \Omega$$

Now a wye-delta transformation is necessary.



Since $R_2=R_3$ and based on the equations for the transformation, the transformed R_Y is given as:


$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \, \Omega)^2}{3 \cdot 100 \, \Omega} = \frac{1}{3} \cdot 100 \, \Omega = 33.33 \, \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \, \Omega + (33.33 \, \Omega + 400 \, \Omega) \parallel (33.33 \, \Omega + 100 \, \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \sim \Omega + 200 \sim \Omega + 200 \sim \Omega) \parallel (100 \sim \Omega + 100 \sim \Omega) \parallel R_{\text{eq}} = \{500 \sim \Omega \cdot 200 \sim \Omega\} \over {500 \sim \Omega + 200 \sim \Omega}$$

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: https://mexle.te.hs-heilbronn.de/electrical_engineering_1/ws2022_exam?rev=1676177819

Last update: 2023/02/12 05:56

