

Exam Winter Semester 2022

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	3
Exercise E1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	6
Exercise E2 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	7
Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)	7
Exercise E3 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	11
Exercise E4 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	11
Exercise E5 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022)	12
Exercise E6 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)	13
Exercise E3 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	15
Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	19
Exercise E5 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	20
Exercise E7 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)	20
Exercise E6 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	24
Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	24
Exercise E4 Charging Capacitors (written test, approx. 16 % of a 60-minute written test,	

WS2022) 25


Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute
written test, WS2022) 26

start

**Exercise E1 Equivalent linear Source
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.
Result


$$\begin{aligned} U_{\text{rs}} &= U_{\text{AB}} = 4.5 \text{ V} \\ R_{\text{i}} &= R_{\text{AB}} = 6 \text{ } \Omega \end{aligned}$$



Calculate the internal resistance R_{i} and the source voltage U_{rs} of an equivalent linear voltage source on the connectors A and B .
 $R_1=5.0 \text{ } \Omega$, $U_2=6.0 \text{ V}$, $R_3= 10 \text{ } \Omega$, $I_4=4.2 \text{ A}$, $R_5=10 \text{ } \Omega$, $R_6=7.5 \text{ } \Omega$, $R_7=15 \text{ } \Omega$
 Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4$$

The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:

$$U_{24} = I_{24} \cdot R_{6135}$$

endstart

Exercise E2 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the phasor voltage \underline{u} (in V) at $t = 30$ ms for the circuit shown in the figure. The components R and X_L shall be given.

After analysis, the following phasor voltage \underline{u} is extracted: $\underline{u} = 10 \angle 45^\circ$ V in phasor notation. $\underline{u} = 10 \cos(\omega t + 45^\circ)$ V in time domain.

Solution
.. Calculate the physical values of the components.
Solution $R = 10 \Omega$, $X_L = 10 \Omega$

Solution
$$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \angle 0^\circ}{4.68 \angle -20^\circ} = 10.68 \angle 20^\circ$$

The current and voltage are in phase since the circuit is purely resistive.
The voltage across the capacitor is $\underline{u}_C = \underline{I} \cdot (-jX_C) = 10.68 \angle 20^\circ \cdot (-j10) = -106.8 \angle 20^\circ$
The voltage across the inductor is $\underline{u}_L = \underline{I} \cdot jX_L = 10.68 \angle 20^\circ \cdot j10 = 106.8 \angle 20^\circ$
The total voltage is $\underline{u} = \underline{u}_C + \underline{u}_L = -106.8 \angle 20^\circ + 106.8 \angle 20^\circ = 0$
With the complex part comes the complex value $\underline{u} = 10 \angle 45^\circ$
 $\varphi = \arctan\left(\frac{\text{Im}(\underline{u})}{\text{Re}(\underline{u})}\right) = \arctan\left(\frac{7.07}{7.07}\right) = 45^\circ$

endstart

Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)

2. Calculate the resulting phasor voltage \underline{u} (in V) at $t = 30$ ms for the circuit shown in the figure. The components R and X_L shall be given. The voltage source is $u(t) = 3.0 \cos(2\pi \cdot 15 \cdot t)$ V.

Solution
This linear source is connected with an inductor of $330 \mu\text{H}$ and a capacitor of $30.22 \mu\text{F}$, all in series.

Result
.. Draw the circuit diagram of the given circuit.
Label all components, voltages, and currents.

```

\begin{align*} Z &= \frac{\hat{U}}{\hat{I}} \quad \hat{I} = \frac{\hat{U}}{Z} \\
\end{align*}
\begin{align*} Z_C &= \frac{1}{2\pi \cdot f \cdot C} \quad \omega = 2\pi \cdot 15 \\
\text{Winkel } \varphi &= \arctan\left(\frac{X_L}{X_C}\right) = \arctan\left(\frac{2\pi \cdot f \cdot L}{\frac{1}{2\pi \cdot f \cdot C}}\right) \\
\end{align*}
\begin{align*} Z &= \sqrt{R^2 + (X_L - X_C)^2} \\
\end{align*}
\begin{align*} Z_C &= \frac{1}{2\pi \cdot f \cdot C} \quad \omega = 2\pi \cdot 15 \\
&\sim \text{kHz} \cdot 330 \sim \mu\text{H} \\
\end{align*}
\begin{align*} \underline{Z} &= R + \underline{Z}_L + \underline{Z}_C \quad \underline{Z} = R + j \\
&\cdot \underline{Z}_L - j \cdot \underline{Z}_C \quad \underline{Z} = R + j \cdot (\underline{Z}_L - \underline{Z}_C) \\
|\underline{Z}| &= \sqrt{R^2 + (\underline{Z}_L - \underline{Z}_C)^2} \\
\end{align*}

```

□□□□□□□□ □510...



endstart

Exercise E3 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)

A series circuit means that the current is constant on every component.
 The equivalent impedance for R and L combined is given by $Z = \sqrt{R^2 + X_L^2}$
 Parallel circuit means that the voltage is the same on R_1 and C_2
 Budget in the parallel circuit: $X_C = \frac{1}{\omega C}$ since ω and C are perpendicular
 $X_C = \frac{1}{2\pi \cdot 40 \cdot 10^{-6}} = 398 \text{ } \Omega$ (It has to, since R_3 is perpendicular to X_C)
 $Z = \sqrt{R_2^2 + X_C^2} = \sqrt{100^2 + 398^2} = 410 \text{ } \Omega$
 Therefore the resulting current of the parallel circuit is given as:
 $I_{3C} = \frac{U}{Z} = \frac{10 \text{ V}}{410 \text{ } \Omega} = 24.4 \text{ mA}$
 Back to the first formula: $R_3 \cdot I_{3C} = X_C \cdot I_{3C} \cdot \frac{I_{3C}}{I_{3R}}$
 $R_3 = X_C \cdot \frac{I_{3C}}{I_{3R}} = 398 \cdot \frac{24.4 \text{ mA}}{100 \text{ mA}} = 97.1 \text{ } \Omega$

Solution

$R_1 = 1.00 \text{ } \Omega$

$R_2 = 10.0 \text{ } \Omega$

A series circuit means that the current is constant on every component.
 The equivalent impedance for R and L combined is given by $Z = \sqrt{R^2 + X_L^2}$
 Parallel circuit means that the voltage is the same on R_1 and C_2
 Budget in the parallel circuit: $X_C = \frac{1}{\omega C}$ since ω and C are perpendicular
 $X_C = \frac{1}{2\pi \cdot 40 \cdot 10^{-6}} = 398 \text{ } \Omega$ (It has to, since R_3 is perpendicular to X_C)
 $Z = \sqrt{R_2^2 + X_C^2} = \sqrt{100^2 + 398^2} = 410 \text{ } \Omega$
 Therefore the resulting current of the parallel circuit is given as:
 $I_{3C} = \frac{U}{Z} = \frac{10 \text{ V}}{410 \text{ } \Omega} = 24.4 \text{ mA}$
 Back to the first formula: $R_3 \cdot I_{3C} = X_C \cdot I_{3C} \cdot \frac{I_{3C}}{I_{3R}}$
 $R_3 = X_C \cdot \frac{I_{3C}}{I_{3R}} = 398 \cdot \frac{24.4 \text{ mA}}{100 \text{ mA}} = 97.1 \text{ } \Omega$

endstart

Exercise E4 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

The heating element is used to heat the wire with a temperature of $180 \text{ } ^\circ\text{C}$.
 Result: power dissipation (= heat flow) of $P=40 \text{ W}$ is necessary.
 Distribute the current in the circuit.
 The Nichrome wire has a resistivity of $1.10 \cdot 10^{-6} \text{ } \Omega \cdot \text{m}$.
 The heating element is 3 m long and has a diameter of 3.57 mm .
 Calculate the resistance R of the heating element.

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad | \quad A = r^2 \cdot \pi = \frac{1}{4} d^2 \cdot \pi \quad R = \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad R = 1.10 \cdot 10^{-6} \text{ } \Omega \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \end{aligned}$$

endstart

Exercise E5 Charging Capacitors
(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (with the real battery) also takes into account the internal resistance of the battery. The voltage across the capacitor is again $U_c(t_2)$ at the moment $t_2 = 1 \text{ ms}$ after closing the switch. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2 = 1 \text{ ms}$ after closing the switch.

Solution
Hint: To solve this, first create an equivalent linear voltage source from U , R_1 , and R_2 .

Solution
The ideal voltage source U is in series with the internal resistance R_1 and the external resistance R_2 . The voltage across the capacitor is $u_c(t)$. On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting R_2 .




The circuit contains a voltage source $U=12 \text{ V}$, a switch S_1 , a resistor of $R_1=20 \text{ } \Omega$ and a capacitor of $C=100 \text{ } \mu\text{F}$.

The switch S_2 to an additional consumer R_2 will be considered to be open for the first asks. At the moment $t_0=0 \text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0)=0 \text{ V}$.

- 1. First do not consider the light bulb - it is not connected to the RC circuit.
- 2. Calculate the point of time t_1 when $u_c(t_1)=0.5 \cdot U$.

Solution



So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_C(t)$ which has to be $u_C(t_1) = 0.5 \cdot U$:

$$u_C(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to $(1 - e^{-t/\tau}) = 0.5$

$$e^{-t/\tau} = 0.5 \implies -t/\tau = \ln(0.5) \implies t = \tau \cdot \ln(0.5)$$



An equivalent linear voltage source can be given with U_s , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$
 The internal resistance is given by substituting the ideal voltage source with its resistance ($R_i = 0 \Omega$, short-circuit).

$$R_i = R_1 \parallel R_B = 10 \Omega$$

$$u_C(t_2) = U_s \cdot (1 - e^{-t_2/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-1 \text{ms}/(10 \Omega \cdot 100 \mu\text{F})})$$


endstart

Exercise E6 Pure Resistor Network Simplification
 (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be solved at 0°C. On the left, $R_1 = R_2 = R_3 = 10 \Omega$ and $R_4 = R_5 = R_6 = 20 \Omega$. The voltage source $U = 10 \text{V}$ is connected between terminals A and B. The current I is the current through R_6 .

Solution

R_{eq} (transfer function) $\omega = 100 \text{ rad/s}$



Since $R_2 = R_3$ and based on the equations for the transformation, the transformed R_Y is given as:


$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2} = \frac{(100 \Omega)^2}{3 \cdot 100 \Omega} = \frac{1}{3} \cdot 100 \Omega = 33.33 \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \Omega + (33.33 \Omega + 400 \Omega) \parallel (33.33 \Omega + 100 \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:


$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \Omega + 200 \Omega + 200 \Omega) \parallel (100 \Omega + 100 \Omega) \parallel R_{\text{eq}} = (500 \Omega) \parallel (200 \Omega) \parallel R_{\text{eq}} = \frac{500 \Omega \cdot 200 \Omega}{500 \Omega + 200 \Omega} \parallel$$

endstart

**Exercise E3 Equivalent linear Source
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.
Result


$$U_{\text{s}} = U_{\text{AB}} = 4.5 \text{ V} \quad R_{\text{i}} = R_{\text{AB}} = 6 \Omega$$




Calculate the internal resistance R_{in} and the source voltage U_{s} of an equivalent linear voltage source on the connectors A and B . $R_1=5.0 \Omega$, $U_2=6.0 \text{ V}$, $R_3=10 \Omega$, $I_4=4.2 \text{ A}$, $R_5=10 \Omega$, $R_6=7.5 \Omega$, $R_7=15 \Omega$. Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4$$

The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:

$$U_{24} = I_{24} \cdot (R_6 || R_7)$$

endstart

Exercise E5 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the phasor voltage \underline{U} and the phasor current \underline{I} in the circuit shown in the figure. The components R and X_L shall be given.

After analysis, the following phasors can be determined: $\underline{U} = 48.2 \angle -19.8^\circ \text{ V}$ and $\underline{I} = 0.24 \angle 4.68^\circ \text{ A}$.
Result
 $\underline{U} = 48.2 \angle -19.8^\circ \text{ V}$
 $\underline{I} = 0.24 \angle 4.68^\circ \text{ A}$

Solution
.. Calculate the physical values of the components.
Solution
 $R = 10 \Omega$
 $X_L = 20 \Omega$

Solution
$$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \angle 0^\circ}{10 + j20} = \frac{50}{\sqrt{10^2 + 20^2}} \angle -63.4^\circ = 1.96 \angle -63.4^\circ \text{ A}$$

The current and voltage are in phase since the circuit is purely resistive.
Resulting voltage $\underline{U} = \underline{I} \cdot \underline{Z} = 1.96 \angle -63.4^\circ \cdot (10 + j20) = 19.6 \angle -63.4^\circ + j39.2 \angle -63.4^\circ = 19.6 \cos(-63.4^\circ) - j19.6 \sin(-63.4^\circ) + j39.2 \cos(-63.4^\circ) - 39.2 \sin(-63.4^\circ) = 7.07 - j17.32 + j14.14 - 17.32 = -10.25 - j3.18 \text{ V}$
The magnitude of the voltage is $U = \sqrt{(-10.25)^2 + (-3.18)^2} = 10.73 \text{ V}$ and the phase is $\varphi = \arctan\left(\frac{-3.18}{-10.25}\right) = 17.3^\circ$.
Resulting current $\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{10.73 \angle 17.3^\circ}{10 + j20} = 0.536 \angle -4.68^\circ \text{ A}$.
With the complex part comes the complex value $\underline{U} = 10.73 \angle 17.3^\circ \text{ V}$ and $\underline{I} = 0.536 \angle -4.68^\circ \text{ A}$.
The phase φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{U})}{\text{Re}(\underline{U})}\right) = \arctan\left(\frac{-3.18}{-10.25}\right) = 17.3^\circ$.

endstart

Exercise E7 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)

2. Calculate the resulting phasor voltage \underline{U} and the phasor current \underline{I} in the circuit shown in the figure. The components R and X_L shall be given.
Result
 $\underline{U} = 48.2 \angle -19.8^\circ \text{ V}$
 $\underline{I} = 0.24 \angle 4.68^\circ \text{ A}$


Solution
This linear source is connected with an inductor of $330 \mu\text{H}$ and a capacitor of $30.22 \mu\text{F}$, all in series.
Result
.. Draw the circuit diagram of the given circuit.
Label all components, voltages, and currents.

```

\begin{align*} Z &= \frac{\hat{U}}{\hat{I}} \quad \hat{I} = \frac{\hat{U}}{Z} \\
\end{align*}
\begin{align*} Z_C &= \frac{1}{2\pi f C} \quad \omega = 2\pi \cdot 15 \\
\omega &= 2\pi \cdot 15 \cdot 10^{-3} = 942 \text{ rad/s} \\
\begin{align*} I &= \frac{U}{Z} = \frac{10 \text{ V}}{\sqrt{R^2 + \left(\frac{1}{\omega C} - \omega L\right)^2}} \\
&= \frac{10}{\sqrt{30^2 + \left(\frac{1}{942 \cdot 10^{-6}} - 942 \cdot 0.02\right)^2}} \\
&= 19.28 \text{ mA} \quad \omega = 19.28 \cdot 2\pi \\
\end{align*}
\begin{align*} Z_C &= \frac{1}{2\pi \cdot 15 \cdot 10^{-3} \cdot 10^{-6}} \\
&= 5555.56 \text{ } \Omega \\
\end{align*}
\underline{Z} = R + j\underline{Z}_L + \underline{Z}_C \quad \underline{Z} = R + j \\
\cdot \underline{Z}_L - j \cdot \underline{Z}_C \quad \underline{Z} = R + j(\underline{Z}_L - \underline{Z}_C) \quad |\underline{Z}| = \\
\sqrt{R^2 + (\underline{Z}_L - \underline{Z}_C)^2}

```

□□□□□□□□ □510...



endstart

Exercise E6 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)

A series circuit means that the current is constant on every component.
 The equivalent impedance for R and L combined is given by $Z = \sqrt{R^2 + X_L^2}$
 Parallel circuit means that the voltage is the same on R_1 and C_1
 The resulting current of the parallel circuit is given as:
 $I_{3C} = I_{3R} + I_{3C}$
 $I_{3C} = \frac{U}{Z} = \frac{U}{\sqrt{R_3^2 + X_{C3}^2}} = \frac{10 \text{ V}}{\sqrt{10^2 + 40^2}} = 0.247 \text{ A}$
 Result: $I_{3R} = I_{3C} = 0.247 \text{ A}$

Solution

$R_1 = 1.00 \text{ } \Omega$

$R_2 = 10.0 \text{ } \Omega$

A series circuit means that the current is constant on every component.
 The equivalent impedance for R and L combined is given by $Z = \sqrt{R^2 + X_L^2}$
 Parallel circuit means that the voltage is the same on R_1 and C_1
 The resulting current of the parallel circuit is given as:
 $I_{3C} = I_{3R} + I_{3C}$
 $I_{3C} = \frac{U}{Z} = \frac{U}{\sqrt{R_3^2 + X_{C3}^2}} = \frac{10 \text{ V}}{\sqrt{10^2 + 40^2}} = 0.247 \text{ A}$
 Result: $I_{3R} = I_{3C} = 0.247 \text{ A}$

endstart

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

The heating element is used to heat the wire with a temperature of $1800 \text{ } ^\circ\text{C}$.
 Result: power dissipation ($=$ heat flow) of $P=40 \text{ W}$ is necessary.
 Calculate the current I needed to operate for heating elements.
 The Nichrome wire has a resistivity of $1.10 \cdot 10^{-6} \text{ } \Omega\text{m}$.
 The heating element is 3 m long and has a diameter of 3.57 mm .
 Calculate the resistance R of the heating element.

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad | \quad A = r^2 \cdot \pi \\ \frac{1}{4} d^2 \cdot \pi \quad R &= \rho \cdot \frac{l}{d^2 \cdot \pi} \quad | \quad R = 1.10 \cdot 10^{-6} \text{ } \Omega \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \end{aligned}$$

endstart

Exercise E4 Charging Capacitors
(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (with the real battery) also takes into account the internal resistance R_1 of the battery. The capacitor is initially uncharged. The switch S_1 is closed at $t_0 = 0 \text{ s}$ and the voltage across the capacitor is again U_c at the moment $t_2 = 1 \text{ ms}$ after closing the switch. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2 = 1 \text{ ms}$ after closing the switch.

Solution
Hint: To solve this, first create an equivalent linear voltage source from U , R_1 , and R_2 .

Solution
The ideal voltage source U is in series with the internal resistance R_1 and the external resistance R_2 . The voltage across the capacitor is $u_c(t) = U \cdot (1 - e^{-t/\tau})$, where $\tau = (R_1 + R_2) \cdot C$.
On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting R_2 .




The circuit contains a voltage source $U = 12 \text{ V}$, a switch S_1 , a resistor of $R_1 = 20 \text{ } \Omega$ and a capacitor of $C = 100 \text{ } \mu\text{F}$.

The switch S_2 to an additional consumer R_2 will be considered to be open for the first asks. At the moment $t_0 = 0 \text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0) = 0 \text{ V}$.

- 1. First do not consider the light bulb - it is not connected to the RC circuit.
- 2. Calculate the point of time t_1 when $u_c(t_1) = 0.5 \cdot U$.

Solution




So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_C(t)$ which has to be $u_C(t_1) = 0.5 \cdot U$:

$$u_C(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to $(1 - e^{-t/\tau}) = 0.5$

$$e^{-t/\tau} = 0.5 \implies -t/\tau = \ln(0.5) \implies t = \tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$$



An equivalent linear voltage source can be given with U , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$
 The internal resistance is given by substituting the ideal voltage source with its resistance ($R_i = 0 \Omega$, short-circuit).

$$R_i = R_1 \parallel R_B = 10 \Omega$$

$$u_C(t_2) = U_s \cdot (1 - e^{-t_2/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-1 \text{ms}/(10 \Omega \cdot 100 \mu\text{F})})$$


endstart

Exercise E3 Pure Resistor Network Simplification
 (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be solved at 0:00 on the 1st of June 2022. $R_1 = R_2 = R_3 = 10 \Omega$ and the voltage source $U = 10 \text{V}$.
 Result given: R_B .

Solution

R_{eq} between A and B



Since $R_2=R_3$ and based on the equations for the transformation, the transformed R_Y is given as:


$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2} = \frac{(100 \Omega)^2}{3 \cdot 100 \Omega} = \frac{1}{3} \cdot 100 \Omega = 33.33 \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \Omega + (33.33 \Omega + 400 \Omega) \parallel (33.33 \Omega + 100 \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B.

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \sim \Omega + 200 \sim \Omega + 200 \sim \Omega) \parallel (100 \sim \Omega + 100 \sim \Omega) \parallel R_{\text{eq}} = \{500 \sim \Omega\} \parallel (200 \sim \Omega) \parallel R_{\text{eq}} = \{500 \sim \Omega \cdot 200 \sim \Omega\} \over {500 \sim \Omega + 200 \sim \Omega}$$

end

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: https://mexle.te.hs-heilbronn.de/electrical_engineering_1/ws2022_exam?rev=1680092006

Last update: **2023/03/29 14:13**

