

# Exam Winter Semester 2022

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E1 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022) .....	3
Exercise E1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) .....	6
Exercise E2 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022) .....	7
Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022) .....	7
Exercise E3 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) .....	10
Exercise E4 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) .....	10
Exercise E5 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022) .....	11
Exercise E6 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022) .....	12
Exercise E3 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022) .....	14
Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) .....	18
Exercise E5 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022) .....	19
Exercise E7 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022) .....	19
Exercise E6 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) .....	22
Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) .....	22
Exercise E4 Charging Capacitors (written test, approx. 16 % of a 60-minute written test,	

WS2022) ..... 23


Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute  
written test, WS2022) ..... 24

1

**Exercise E1 Equivalent linear Source  
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.  
Result

$$\begin{aligned} U_{\text{rs}} &= U_{\text{AB}} = 4.5 \text{ V} \\ R_{\text{i}} &= R_{\text{AB}} \\ &= 6 \Omega \end{aligned}$$



Calculated the internal resistance  $R_{\text{i}}$  and the source voltage  $U_{\text{rs}}$  of an equivalent linear voltage source on the connectors  $\text{A}$  and  $\text{B}$ .  
 $R_1=5.0 \Omega$ ,  $U_2=6.0 \text{ V}$ ,  $R_3= 10 \Omega$ ,  $I_4=4.2 \text{ A}$ ,  $R_5=10 \Omega$ ,  $R_6=7.5 \Omega$ ,  $R_7=15 \Omega$   
 Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of  $U_2$  and  $R_1$  can be transformed into a current source  $I_2 = \frac{U_2}{R_1}$  and  $R_1$ :



Now a lot of them can be combined. The resistors  $R_1$ ,  $R_3$ ,  $R_5$  are in parallel, like also  $I_2$  and  $I_4$ :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4 = \frac{U_2}{R_1} - I_4$$

The resulting circuit can again be transformed:



Here, the  $U_{24}$  is calculated by  $I_{24}$  as the following:

$$U_{24} = I_{24} \cdot (R_6 + R_7)$$

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - I_4 \cdot R_1 || R_3 || R_5$$

On the right side of the last circuit, there is a voltage divider given by  $R_{135}$ ,  $R_6$ , and  $R_7$ .

Therefore the voltage between  $A$  and  $B$  is given as:

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - \left( \frac{U_2}{R_1} - I_4 \right) \cdot \left( R_1 || R_3 || R_5 \right)$$

For the internal resistance  $R_i$  the ideal voltage source is substituted by its resistance ( $=0 \Omega$ , so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with  $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$ :

$$U_{AB} = \left( \frac{6.0 \text{ V}}{5.0 \Omega} \right) - 4.2 \text{ A} \cdot \left( \frac{15 \Omega \cdot 2.5 \Omega}{7.5 \Omega + 15 \Omega + 2.5 \Omega} \right)$$

$$R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

**Exercise E1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)**

2. A refrigerator, explained in the effect of resistance on refrigeration systems, has a resistance of  $15 \Omega$  at  $25^\circ\text{C}$  and a temperature coefficient of  $\alpha = 0.01 \text{ K}^{-1}$  and  $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$ .

Its temperature coefficients are:  $\alpha = 0.01 \text{ K}^{-1}$  and  $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$ .

**Result**  
The temperature inside the refrigeration system can reach down to  $-40^\circ\text{C}$ .

Calculate the resistance of the thermistor at  $-40^\circ\text{C}$ .

The power transferred to the resistor is  $P = U \cdot I$  and  $I = \frac{U}{R}$ . Therefore, a solution is to increase the heat flow up the refrigeration system.

Therefore, with constant  $U$  and increasing  $R$  the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

$$\text{with } \Delta T = T_{\text{end}} - T_{\text{start}} \implies R = 10 \Omega \cdot \left( 1 + 0.01 \text{ K}^{-1} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \cdot 10^{-6} \text{ K}^{-2} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2 \right)$$

### Exercise E2 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the complex impedance  $Z$  of the circuit shown in the figure. The voltage  $u(t) = 3.0 \cdot \sin(2\pi \cdot 15 \cdot t)$  V and the current  $i(t) = 0.24 \cdot \sin(2\pi \cdot 15 \cdot t - \varphi)$  A shall be given.

After analysis, the following complex impedance  $Z$  shall be extracted and the phase angle  $\varphi$  in phase (in degrees) shall be determined.

Solution  
.. Calculate the physical values of the two components.  
Solution  $R = 10 \Omega$  and  $X_L = 2\pi \cdot 15 \cdot 0.2 = 1.88 \Omega$

Solution

$$\underline{I} = \frac{\underline{U}}{\underline{Z}} \implies \underline{Z} = \frac{\underline{U}}{\underline{I}} = \frac{3.0 \angle 0^\circ}{0.24 \angle -\varphi} = 12.5 \angle \varphi$$

The voltage  $u(t) = 3.0 \cdot \sin(2\pi \cdot 15 \cdot t)$  V and the current  $i(t) = 0.24 \cdot \sin(2\pi \cdot 15 \cdot t - \varphi)$  A shall be given. The resulting impedance  $Z$  shall be determined.

Therefore, the component  $R$  shall be determined with the same procedure as for the inductor.  $Z_R = R = 10 \Omega$  and  $Z_L = j\omega L = j1.88 \Omega$ . The resulting impedance  $Z$  shall be determined.

With the complex part  $Z = R + jX_L$  the physical values shall be determined.  $Z = 10 + j1.88 \Omega$ . The phase angle  $\varphi$  shall be calculated as  $\varphi = \arctan\left(\frac{X_L}{R}\right) = \arctan\left(\frac{1.88}{10}\right) = 10.5^\circ$ .

The phase angle  $\varphi$  shall be calculated as  $\varphi = \arctan\left(\frac{X_L}{R}\right) = \arctan\left(\frac{1.88}{10}\right) = 10.5^\circ$ .

### Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)

2. Calculate the complex impedance  $Z$  of the circuit shown in the figure. The voltage  $u(t) = 3.0 \cdot \sin(2\pi \cdot 15 \cdot t)$  V and the current  $i(t) = 0.24 \cdot \sin(2\pi \cdot 15 \cdot t - \varphi)$  A shall be given.

After analysis, the following complex impedance  $Z$  shall be extracted and the phase angle  $\varphi$  in phase (in degrees) shall be determined.

Solution  
Result  
.. Draw the circuit diagram of the given circuit.  
Solution  $Z = 10 + j1.88 \Omega$

With the complex part  $Z = R + jX_L$  the physical values shall be determined.  $Z = 10 + j1.88 \Omega$ . The phase angle  $\varphi$  shall be calculated as  $\varphi = \arctan\left(\frac{X_L}{R}\right) = \arctan\left(\frac{1.88}{10}\right) = 10.5^\circ$ .

The phase angle  $\varphi$  shall be calculated as  $\varphi = \arctan\left(\frac{X_L}{R}\right) = \arctan\left(\frac{1.88}{10}\right) = 10.5^\circ$ .





**Exercise E3 Impedances at different Frequencies**  
**(written test, approx. 18 % of a 60-minute written test, WS2022)**

2. A series circuit consists of a resistor with a resistance of  $R_1 = 1.00 \text{ k}\Omega$ , a capacitor with a capacitance of  $C_1 = 40 \text{ nF}$ , and an inductor with an inductance of  $L_1 = 4.7 \text{ }\mu\text{H}$ . The circuit is connected to an AC voltage source with a voltage of  $U = 10 \text{ V}$  and a frequency of  $f = 4 \text{ MHz}$ . Calculate the absolute value of the impedance  $|Z|$  of the circuit.

Solution

$|Z| = \sqrt{R^2 + (X_L - X_C)^2}$

$|Z| = \sqrt{(1.00 \text{ k}\Omega)^2 + (2\pi \cdot 4 \text{ MHz} \cdot 4.7 \text{ }\mu\text{H} - \frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}})^2}$

$|Z| = \sqrt{(1000 \text{ }\Omega)^2 + (111.63 \text{ }\Omega - 994.72 \text{ }\Omega)^2}$

$|Z| = \sqrt{(1000 \text{ }\Omega)^2 + (-883.09 \text{ }\Omega)^2}$

$|Z| = \sqrt{1000000 \text{ }\Omega^2 + 779840 \text{ }\Omega^2}$

$|Z| = \sqrt{1779840 \text{ }\Omega^2}$

$|Z| = 1334.11 \text{ }\Omega$

A series circuit means that the current is constant on every component.  
 The equivalent impedance for  $R$  and  $L$  combined is given by  $|Z| = \sqrt{R^2 + X_L^2}$   
 Parallel circuit means that the voltage is the same on  $R_1$  and  $C_1$   $\frac{1}{|Z|} = \frac{1}{R} + \frac{1}{X_C}$   
 $|Z| = \frac{R \cdot X_C}{R + X_C}$  since  $U$  and  $I$  are perpendicular  
 $|Z| = \frac{10 \text{ V}}{\frac{1}{1000 \text{ }\Omega} + \frac{1}{994.72 \text{ }\Omega}}$  gets clean and  
 $|Z| = 500 \text{ }\Omega$  is perpendicular to  $|Z| = 1000 \text{ }\Omega$  (It has to, since  $R$  is perpendicular to  $X_C$ )  
 $|Z| = \sqrt{(1000 \text{ }\Omega)^2 + (500 \text{ }\Omega)^2} = 1118 \text{ }\Omega$   
 Therefore, the resulting current of the parallel circuit is given as:  
 $I = \frac{U}{|Z|} = \frac{10 \text{ V}}{1118 \text{ }\Omega} = 8.94 \text{ mA}$   
 This current is perpendicular to  $U$  and  $I$  is perpendicular to  $U$   
 $I = \sqrt{I_1^2 + I_2^2} = \sqrt{(8.94 \text{ mA})^2 + (8.94 \text{ mA})^2} = 12.57 \text{ mA}$   
 $I = \sqrt{2} \cdot 8.94 \text{ mA} = 12.57 \text{ mA}$   
 Back to the first formula:  $|Z| = \sqrt{R^2 + (X_L - X_C)^2}$   
 $|Z| = \sqrt{(1000 \text{ }\Omega)^2 + (111.63 \text{ }\Omega - 994.72 \text{ }\Omega)^2}$   
 $|Z| = \sqrt{(1000 \text{ }\Omega)^2 + (-883.09 \text{ }\Omega)^2}$   
 $|Z| = \sqrt{1000000 \text{ }\Omega^2 + 779840 \text{ }\Omega^2}$   
 $|Z| = \sqrt{1779840 \text{ }\Omega^2}$   
 $|Z| = 1334.11 \text{ }\Omega$

**Exercise E4 Resistance of a Wire by Resistivity**  
**(written test, approx. 6 % of a 60-minute written test, WS2022)**

2. Heating elements are used to heat the oven with a temperature of  $180 \text{ }^\circ\text{C}$ . The electric power dissipation (= heat flow) of  $P = 40 \text{ W}$  is necessary.  
 Calculate the current  $I$  needed to operate the heating elements.

The Nichrome wire has a resistivity of  $\rho = 1.10 \cdot 10^{-6} \text{ }\Omega \cdot \text{m}$ .  
 The heating element is  $l = 3 \text{ m}$  long and has a diameter of  $d = 3.57 \text{ mm}$ .  
 Calculate the resistance  $R$  of the heating element.

Solution

$R = \frac{\rho \cdot l}{A}$

$R = \frac{1.10 \cdot 10^{-6} \text{ }\Omega \cdot \text{m} \cdot 3 \text{ m}}{\pi \cdot (\frac{3.57 \text{ mm}}{2})^2}$

$R = 0.033 \text{ }\Omega$

$$\sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \cdot \Omega}} \quad \text{align*}$$

$$\begin{aligned} R &= \rho \cdot l \cdot \frac{1}{A} \quad \& \quad | \quad \text{with } A = r^2 \cdot \pi = \\ &= \frac{1}{4} \cdot d^2 \cdot \pi \quad \& \quad \rho = \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ &= 1.10 \cdot 10^{-6} \cdot \Omega \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \quad \& \quad \end{aligned}$$


**Exercise E5 Charging Capacitors**  
**(written test, approx. 16 % of a 60-minute written test, WS2022)**

The circuit (with the light bulb) is a series of  $R_1$  and  $R_2$  and a capacitor  $C$  and a switch  $S_1$  and a switch  $S_2$ . The voltage across the capacitor is again  $0 \text{ V}$  at the moment  $t_0 = 0 \text{ s}$  when the switch  $S_1$  is closed. Calculate the voltage  $u_c(t_2)$  across the capacitor at  $t_2 = 1 \text{ ms}$  after closing the switch.

**Solution**  
 Hint: To solve this, first create an equivalent linear voltage source from  $U$ ,  $R_1$ , and  $R_2$ .

**Solution**  
 The ideal voltage source  $U$  is in series with  $R_1$  and  $R_2$ . The voltage  $u_c$  is independent of this series  $(U - u_c)^2$ .

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting  $S_2$ .




The circuit contains a voltage source  $U = 12 \text{ V}$ , a switch  $S_1$ , a resistor of  $R_1 = 20 \text{ }\Omega$  and a capacitor of  $C = 100 \text{ }\mu\text{F}$ .

The switch  $S_2$  to an additional consumer  $R_2$  will be considered to be open for the first tasks. At the moment  $t_0 = 0 \text{ s}$  the switch  $S_1$  is closed, the voltage across the capacitor is  $u_c(t_0) = 0 \text{ V}$ .

... First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time  $t_1$  when  $u_c(t_1) = 0.5 \cdot U$ .

**Solution**





Since  $R_2=R_3$  and based on the equations for the transformation, the transformed  $R_Y$  is given as:


$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \, \Omega)^2}{3 \cdot 100 \, \Omega} = \frac{1}{3} \cdot 100 \, \Omega = 33.33 \, \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \, \Omega + (33.33 \, \Omega + 400 \, \Omega) \parallel (33.33 \, \Omega + 100 \, \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance  $R_{\text{eq}}$  between  $A$  and  $B$ .

Solution




The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_{-1}) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \Omega + 200 \Omega + 200 \Omega) \parallel (100 \Omega + 100 \Omega) \parallel R_{\text{eq}} = (500 \Omega) \parallel (200 \Omega) \parallel R_{\text{eq}} = \frac{500 \Omega \cdot 200 \Omega}{500 \Omega + 200 \Omega} \parallel$$

**Exercise E3 Equivalent linear Source  
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.  
Result

$$U_{\text{s}} = U_{\text{AB}} = 4.5 \text{ V} \quad R_{\text{i}} = R_{\text{AB}} = 6 \Omega$$




Calculate the internal resistance  $R_{int}$  and the source voltage  $U_{s}$  of an equivalent linear voltage source on the connectors  $A$  and  $B$ .  $R_1=5.0 \Omega$ ,  $U_2=6.0 \text{ V}$ ,  $R_3=10 \Omega$ ,  $I_4=4.2 \text{ A}$ ,  $R_5=10 \Omega$ ,  $R_6=7.5 \Omega$ ,  $R_7=15 \Omega$ . Use equivalent sources in order to simplify the circuit!

### Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of  $U_2$  and  $R_1$  can be transformed into a current source  $I_2 = \frac{U_2}{R_1}$  and  $R_1$ :



Now a lot of them can be combined. The resistors  $R_1$ ,  $R_3$ ,  $R_5$  are in parallel, like also  $I_2$  and  $I_4$ : 
$$R_{135} = R_1 || R_3 || R_5$$
 
$$I_{24} = I_2 - I_4 = \frac{U_2}{R_1} - I_4$$
 The resulting circuit can again be transformed:



Here, the  $U_{24}$  is calculated by  $I_{24}$  as the following: 
$$U_{24}$$

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - I_4 \cdot (R_1 || R_3 || R_5)$$

On the right side of the last circuit, there is a voltage divider given by  $R_{135}$ ,  $R_6$ , and  $R_7$ .

Therefore the voltage between  $A$  and  $B$  is given as:

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - I_4 \cdot (R_1 || R_3 || R_5)$$

For the internal resistance  $R_i$  the ideal voltage source is substituted by its resistance ( $=0 \Omega$ , so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with  $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$ :

$$U_{AB} = \left( \frac{6.0 \text{ V}}{5.0 \Omega} \right) - 4.2 \text{ A} \cdot (15 \Omega \cdot 2.5 \Omega) / (7.5 \Omega + 15 \Omega + 2.5 \Omega)$$

$$R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

**Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)**

2. A refrigerator has a resistor with a resistance of  $R_0 = 10 \Omega$  at  $25^\circ\text{C}$ . Its temperature coefficients are:  $\alpha = 0.01 \text{ K}^{-1}$  and  $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$ .

Calculate the resistance of the resistor at  $-40^\circ\text{C}$ .

**Result**

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

$$R = 10 \Omega \cdot (1 + 0.01 \text{ K}^{-1} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \cdot 10^{-6} \text{ K}^{-2} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2)$$

The power of the resistor  $P = U^2 / R$  and  $Q = P \cdot t$ . Therefore, a solution is to use a heat pump to heat the refrigerator system. Therefore, with constant  $U$  and increasing  $R$  the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

$$R = 10 \Omega \cdot (1 + 0.01 \text{ K}^{-1} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \cdot 10^{-6} \text{ K}^{-2} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2)$$

**Exercise E5 Analyzing complex Impedances**  
 (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the complex power  $\underline{S}$  (W and var) of the load  $\underline{Z}$  through the components.  $\underline{S}_R$  and  $\underline{S}_L$  shall be given.

After analysis, the full load impedance  $\underline{Z}$  can be extracted and brought in phasor notation  $\underline{Z} = |Z| \cdot e^{j\varphi}$  with  $\varphi = \varphi(\omega)$ .

Solution  
 .. Calculate the physical values of the load components.  
 Solution  $R = 10 \Omega$ ,  $L = 10 \text{ mH}$ ,  $C = 10 \text{ nF}$

Solution

$$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \text{ V}}{0.24 - j4.68 \text{ } \Omega} = 208.33 \text{ A} \cdot e^{j1.107 \text{ rad}}$$
 The voltage  $\underline{U}$  is the phasor of  $u(t) = 50 \text{ V} \cdot \cos(\omega t)$ .  
 The resulting impedance  $\underline{Z} = 0.24 - j4.68 \text{ } \Omega$ .  
 Therefore, the component  $4.68 \text{ } \Omega$  is a capacitor with the same absolute value of  $4.68 \text{ } \Omega$  as the inductor  $4.68 \text{ } \Omega$ .  
 Impedance  $\underline{Z} = R + jX_L - jX_C = 10 \text{ } \Omega + j31.416 \text{ } \Omega - j36.76 \text{ } \Omega = 10 - j5.344 \text{ } \Omega$   

$$\underline{S} = \underline{U} \cdot \underline{I}^* = 50 \text{ V} \cdot (208.33 \text{ A})^* \cdot e^{-j1.107 \text{ rad}} = 10416.67 \text{ VA} \cdot e^{-j1.107 \text{ rad}}$$

$$\underline{S} = P + jQ = 10416.67 \text{ W} - j11070 \text{ var}$$
 The active power  $P = 10416.67 \text{ W}$  and the reactive power  $Q = -11070 \text{ var}$ .  
 With the complex part  $\varphi = \arctan\left(\frac{-5.344}{10}\right) = -28.36^\circ$   

$$\varphi = \arctan\left(\frac{-5.344}{10}\right) = -28.36^\circ$$
 The phase  $\varphi$  can be calculated as  $\varphi = \arctan\left(\frac{-5.344}{10}\right) = -28.36^\circ$

**Exercise E7 Complex Impedance Circuit**  
 (written test, approx. 15 % of a 60-minute written test, WS2022)

2. Calculate the circuit impedance  $\underline{Z}$  for  $\omega = 15 \text{ kHz}$ .  $\underline{Z}_C$  and  $\underline{Z}_L$  shall be given.  
 Result  $\underline{Z} = 19.8 - j48.2 \text{ } \Omega$   
 The voltage source  $u(t) = 3.0 \text{ V} \cdot \sin(2\pi \cdot 15 \text{ kHz} \cdot t)$   
 The circuit consists of a resistor  $R = 10 \text{ } \Omega$ , an inductor  $L = 330 \text{ } \mu\text{H}$ , and a capacitor  $C = 0.22 \text{ } \mu\text{F}$ .

Solution  
 .. Draw the circuit diagram of the given circuit.

Result  
 .. Draw the circuit diagram of the given circuit.  
 Solution  $\underline{Z} = 19.8 - j48.2 \text{ } \Omega$


With  $\underline{Z} = 19.8 - j48.2 \text{ } \Omega$   

$$\underline{Z} = R + jX_L - jX_C = 10 \text{ } \Omega + j330 \text{ } \mu\text{H} \cdot \omega - j0.22 \text{ } \mu\text{F} \cdot \omega$$

$$\underline{Z} = 10 \text{ } \Omega + j330 \text{ } \mu\text{H} \cdot 15 \text{ kHz} - j0.22 \text{ } \mu\text{F} \cdot 15 \text{ kHz}$$

$$\underline{Z} = 10 \text{ } \Omega + j4.95 \text{ } \Omega - j33 \text{ } \Omega = 10 - j28.05 \text{ } \Omega$$





**Exercise E6 Impedances at different Frequencies**  
**(written test, approx. 18 % of a 60-minute written test, WS2022)**

2. A series circuit consists of a resistor with a resistance of  $R_1 = 1.00 \text{ k}\Omega$ , a capacitor with a capacitance of  $C_1 = 40 \text{ nF}$ , and an inductor with an inductance of  $L_1 = 4.7 \text{ }\mu\text{H}$ . The circuit is connected to an AC voltage source with a voltage of  $U = 10 \text{ V}$  and a frequency of  $f = 4 \text{ MHz}$ . Calculate the absolute value of the impedance  $|Z|$  of the circuit.

Solution

$$|Z| = \sqrt{R_1^2 + (X_L - X_C)^2}$$

$$|Z| = \sqrt{(1.00 \text{ k}\Omega)^2 + (2\pi \cdot 4 \text{ MHz} \cdot 4.7 \text{ }\mu\text{H} - \frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}})^2}$$

A series circuit means that the current is constant on every component.  
 The equivalent impedance for  $R$  and  $L$  combined is given by  $Z = R + jX_L$   
 Parallel circuit means that the voltage is the same on  $R$  and  $C$   $Z = \frac{R \cdot X_C}{R + jX_C}$   
 $|Z| = \frac{R \cdot X_C}{\sqrt{R^2 + X_C^2}}$  since  $\underline{U} \perp \underline{I}$  and  $\underline{U} \perp \underline{I}$  is perpendicular to  $\underline{R}$  this can be simplified to  $|Z| = \frac{R \cdot X_C}{\sqrt{R^2 + X_C^2}}$   
 $\underline{U} \perp \underline{I}$  is perpendicular to  $\underline{R} + jX_C$  (It has to, since  $R$  is perpendicular to  $X_C$ )  
 $\underline{U} \perp \underline{I} \Rightarrow \underline{U} \cdot \underline{I} = 0 \Rightarrow \underline{U} \cdot (R + jX_C) = 0 \Rightarrow R \cdot \underline{U} + jX_C \cdot \underline{U} = 0$   
 Therefore, the resulting current of the parallel circuit is given as:  

$$\underline{I} = \frac{\underline{U}}{R} + \frac{\underline{U}}{jX_C} = \underline{U} \left( \frac{1}{R} - \frac{j}{X_C} \right)$$
  

$$|\underline{I}| = \frac{U}{R} \sqrt{1 + \left( \frac{R}{X_C} \right)^2}$$
  
 This can be rearranged to  $R = \frac{U}{|\underline{I}|} \sqrt{1 + \left( \frac{R}{X_C} \right)^2}$   

$$R^2 = \frac{U^2}{|\underline{I}|^2} \left( 1 + \frac{R^2}{X_C^2} \right)$$
  

$$R^2 \left( 1 - \frac{U^2}{|\underline{I}|^2 X_C^2} \right) = \frac{U^2}{|\underline{I}|^2}$$
  

$$R = \frac{U}{|\underline{I}|} \frac{1}{\sqrt{1 - \frac{U^2}{|\underline{I}|^2 X_C^2}}}$$
  
 Back to the first formula: 
$$|Z| = \sqrt{R^2 + (X_L - X_C)^2}$$
  

$$|Z| = \sqrt{\left( \frac{U}{|\underline{I}|} \frac{1}{\sqrt{1 - \frac{U^2}{|\underline{I}|^2 X_C^2}}} \right)^2 + (X_L - X_C)^2}$$

**Exercise E1 Resistance of a Wire by Resistivity**  
**(written test, approx. 6 % of a 60-minute written test, WS2022)**

2. For heating elements used to heat the oven at a temperature of  $180 \text{ }^\circ\text{C}$ , an electric power dissipation (= heat flow) of  $P = 40 \text{ W}$  is necessary.  
 Calculate the current  $I$  needed to operate the heating elements.  
 The Nichrome wire has a resistivity of  $\rho = 1.10 \cdot 10^{-6} \text{ }\Omega \cdot \text{m}$ .  
 The heating element is  $l = 3 \text{ m}$  long and has a diameter of  $d = 3.57 \text{ mm}$ .  
 Calculate the resistance  $R$  of the heating element.

Solution

$$P = U \cdot I = R \cdot I^2 \quad \Rightarrow \quad I = \sqrt{\frac{P}{R}}$$

$$\sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \quad \text{align*}$$

$$\begin{aligned} R &= \rho \cdot l \cdot \frac{1}{A} \quad \& \quad | \quad \text{with } A = r^2 \cdot \pi = \\ &= \frac{1}{4} d^2 \cdot \pi \quad \& \quad R = \rho \cdot l \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ &= 1.10 \cdot 10^{-6} \text{ } \Omega \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \quad \& \quad \end{aligned}$$


**Exercise E4 Charging Capacitors**  
 (written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (with the light bulb) is a series of  $R_1$  and  $R_2$  and a capacitor  $C$  and a switch  $S_1$  and a switch  $S_2$ . The voltage across the capacitor is again  $0 \text{ V}$  at the moment  $t_0 = 0 \text{ s}$  when the switch  $S_1$  is closed. Calculate the voltage  $u_c(t_2)$  across the capacitor at  $t_2 = 1 \text{ ms}$  after closing the switch.

**Solution:** To solve this, first create an equivalent linear voltage source from  $U$ ,  $R_1$ , and  $R_2$ .

The ideal voltage source  $U$  is in series with  $R_1$  and  $R_2$ . The voltage  $u_c$  is independent of this series.

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting  $S_1$ .




The circuit contains a voltage source  $U = 12 \text{ V}$ , a switch  $S_1$ , a resistor of  $R_1 = 20 \text{ } \Omega$  and a capacitor of  $C = 100 \text{ } \mu\text{F}$ .

The switch  $S_2$  to an additional consumer  $R_2$  will be considered to be open for the first tasks. At the moment  $t_0 = 0 \text{ s}$  the switch  $S_1$  is closed, the voltage across the capacitor is  $u_c(t_0) = 0 \text{ V}$ .

.. First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time  $t_1$  when  $u_c(t_1) = 0.5 \cdot U$ .

**Solution**




An equivalent linear voltage source can be given with  $U_s$ ,  $R_1$ , and  $R_B$  as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is:  $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$  The internal resistance is given by substituting the ideal voltage source with its resistance ( $R = 0 \Omega$ , short-circuit).

$$R_i = R_1 \parallel R_B = 10 \Omega$$

$$u_c(t) = U_s \cdot (1 - e^{-t/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-t/(10 \Omega \cdot 100 \mu F)})$$

The following formula describes the time course of  $u_c(t)$  which has to be  $u_c(t_1) = 0.5 \cdot U$ : 
$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to  $(1 - e^{-t/\tau}) = 0.5 \implies e^{-t/\tau} = 0.5 \implies t/\tau = \ln(0.5) \implies t = \tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$



**Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)**

The following shall be solved at a rate of  $R_1 = R_2 = R_3 = 10 \Omega$  and the voltage  $U = 10V$  is given.  $R_B$ .

Solution

$$R_{\text{eq}} = 132.8 \Omega$$

Now a wye-delta transformation is necessary.



Since  $R_2=R_3$  and based on the equations for the transformation, the transformed  $R_Y$  is given as:


$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \, \Omega)^2}{3 \cdot 100 \, \Omega} = \frac{1}{3} \cdot 100 \, \Omega = 33.33 \, \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \, \Omega + (33.33 \, \Omega + 400 \, \Omega) \parallel (33.33 \, \Omega + 100 \, \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance  $R_{\text{eq}}$  between  $A$  and  $B$ .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \sim \Omega + 200 \sim \Omega + 200 \sim \Omega) \parallel (100 \sim \Omega + 100 \sim \Omega) \parallel R_{\text{eq}} = \{500 \sim \Omega\} \parallel (200 \sim \Omega) \parallel R_{\text{eq}} = \{500 \sim \Omega \cdot 200 \sim \Omega\} \over {500 \sim \Omega + 200 \sim \Omega}$$

From:

<https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:

[https://mexle.te.hs-heilbronn.de/electrical\\_engineering\\_1/ws2022\\_exam?rev=1680241578](https://mexle.te.hs-heilbronn.de/electrical_engineering_1/ws2022_exam?rev=1680241578)

Last update: **2023/03/31 07:46**

