

# Resistance measurement

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Resistance measurement ..... 2  
  Direct resistance measurement ..... 2  
  Indirect resistance measurement ..... 3

## Resistance measurement

Procedure for resistance measurement:

1. Set the measuring device to resistance measurement
2. Connect the resistance to be measured to the corresponding sockets on the measuring device (the measuring device sockets labeled COM and  $\Omega$ )
3. Read the measured value

There are different types of resistance measurement:

- **direct** resistance measurement
- **indirect** resistance measurement

### Direct resistance measurement

Determine the nominal and measured values of the resistance for  $R_{\text{1}}$  (brown, green, orange),  $R_{\text{2}}$  (yellow, violet, red),  $R_{\text{3}}$  (red, violet, red) and the incandescent lamp  $R_{\text{L}}$ . Also measure the approximate resistance  $R_{\text{K}}$  of your body from your right to your left hand.

	$R_{\text{1}}$	$R_{\text{2}}$	$R_{\text{3}}$	$R_{\text{L}}$	$R_{\text{K}}$
nominal value					
measured value					

Tab. 1: Direct resistance measurement

How do you explain the deviation between  $R_{\text{L,nominal}}$  and  $R_{\text{L,meas}}$ ?

What consequences can  $R_{\text{K}}$  have?

Now determine the series and parallel connections of resistors  $R_{\text{1}}$ ,  $R_{\text{2}}$  and  $R_{\text{3}}$ .

Specify the formulas used:

$R_{\text{serial}} =$

$R_{\text{parallel}} (= R_{\text{a}} || R_{\text{b}}) =$

	$R_1+R_2$	$R_1+R_3$	$R_2+R_3$	$R_1    R_2$	$R_1    R_3$	$R_2    R_3$
calculated						
measured						

Text is not SVG - cannot display

Tab. 2: Series and parallel connections

**Indirect resistance measurement**

The resistances can also be determined by measuring the current/voltage.

**Ohm's law: In an electrical circuit, the current increases with increasing voltage and decreases with increasing resistance.**

$I = \frac{U}{R}$

Build the measuring circuit shown in [figure 1](#) for each of the three resistors and set the voltage on the power supply to  $\sim 12 \text{ V}$ .



Fig. 1: Indirect resistance measurement

Measure  $U_{\text{nm}}$  [V] and  $I_{\text{nm}}$  [mA]. Calculate  $R_{\text{nm}}$  [k $\Omega$ ] from these values.

$I_{\text{nm}}$	$U_{\text{nm}}$	$R_{\text{nm}}$	$I_{\text{nm}}$	$U_{\text{nm}}$	$R_{\text{nm}}$	$I_{\text{nm}}$	$U_{\text{nm}}$	$R_{\text{nm}}$

Tab. 3: Indirect resistance measurement

From:

<https://mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

[https://mexle.te.hs-heilbronn.de/lab\\_electrical\\_engineering/1\\_resistors/resistance-measurement?rev=1773110639](https://mexle.te.hs-heilbronn.de/lab_electrical_engineering/1_resistors/resistance-measurement?rev=1773110639)

Last update: **2026/03/10 03:43**

