

# task\_70jig4yzznocarsq\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 2

temperature dependent resistance, power, heat, exam ee1 WS2022

**Exercise E2 Temperature-dependent Resistance  
(written test, approx. 6 % of a 60-minute written test, WS2022)**

A. The circuit diagram shows a thermistor with a temperature-dependent resistance. The thermistor has a resistance of  $R_0 = 10 \text{ k}\Omega$  at  $T_0 = 25^\circ\text{C}$ . Its temperature coefficients are:  $\alpha = 0.01 \text{ 1/K}$  and  $\beta = 71 \cdot 10^{-6} \text{ 1/K}^2$ .

Result: The temperature inside the refrigeration system can reach down to  $-40^\circ\text{C}$ .

Calculate the resistance of the thermistor at  $-40^\circ\text{C}$ .

Resistance of the resistor  $R$  depends on the current  $I$  and generated heat. Therefore, a solution exists for the heat flow.

Therefore, with constant  $U$  and increasing  $R$  the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2) \quad | \quad \Delta T = T_{\text{end}} - T_{\text{start}}$$
$$R = 10 \text{ k}\Omega \cdot (1 + 0.01 \text{ 1/K} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \cdot 10^{-6} \text{ 1/K}^2 \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2)$$

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: [https://mexle.te.hs-heilbronn.de/electrical\\_engineering\\_and\\_electronics/task\\_70jig4yzznocarsq\\_with\\_calculation](https://mexle.te.hs-heilbronn.de/electrical_engineering_and_electronics/task_70jig4yzznocarsq_with_calculation)

Last update: 2023/04/02 00:44

