

# rechnung\_betragundphase\_umkehrintegrator

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

$U_A = -\{1 \over R \cdot C\} \cdot \int_{t_0}^{t_1} \color{blue}\{U_E(t)\} \cdot dt + U_{A0}$	insert sine function	$\color{blue}\{U_E(t)\} = \hat{U}_E \cdot \sin(\omega \cdot t)$
$U_A = -\{1 \over R \cdot C\} \cdot \int_{t_0}^{t_1} \color{blue}\{\sin(\omega \cdot t)\} \cdot dt + U_{A0}$	insert root function with \limits	$\int \sin(a \cdot x) \cdot dx = -\{1 \over a\} \cdot \cos(a \cdot x)$
$U_A = -\{1 \over R \cdot C\} \cdot \int_{t_0}^{t_1} \color{blue}\{\cos(\omega \cdot t)\} \cdot dt + U_{A0}$	put constant before \ integral	
$U_A = \{1 \over \omega \cdot R \cdot C\} \cdot \int_{t_0}^{t_1} \color{blue}\{\cos(\omega \cdot t)\} \cdot dt + U_{A0}$	insert limits	$t_0=0, t_1=t$
$U_A = \{1 \over \omega \cdot R \cdot C\} \cdot \cos(\omega \cdot t) - \color{blue}\{\cos(0)\} + U_{A0}$	$\color{blue}\{\cos(0)\}=1$	
$U_A = \color{blue}\{\hat{U}_E\} \cdot \int_{t_0}^{t_1} \color{blue}\{\cos(\omega \cdot t) - 1\} \cdot dt + U_{A0}$	multiply	
$U_A = \{1 \over \omega \cdot R \cdot C\} \cdot \int_{t_0}^{t_1} \color{blue}\{\cos(\omega \cdot t) - 1\} \cdot dt + U_{A0}$	consider the \non-cosine terms	
$U_A = \{1 \over \omega \cdot R \cdot C\} \cdot \int_{t_0}^{t_1} \color{blue}\{\cos(\omega \cdot t) - 1\} \cdot dt + U_{A0}$	This part is independent in time. Since we assume purely sinusoidal quantities, the for the initial voltage of the capacitor must be:	$U_{C0} = U_{A0} = \color{blue}\{\hat{U}_E\} \cdot \int_{t_0}^{t_1} \color{blue}\{\cos(\omega \cdot t) - 1\} \cdot dt$
$U_A = \{1 \over \omega \cdot R \cdot C\} \cdot \int_{t_0}^{t_1} \color{blue}\{\cos(\omega \cdot t) - 1\} \cdot dt + U_{A0}$		

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: [https://mexle.te.hs-heilbronn.de/circuit\\_design/rechnung\\_betragundphase\\_umkehrintegrator?rev=1632539851](https://mexle.te.hs-heilbronn.de/circuit_design/rechnung_betragundphase_umkehrintegrator?rev=1632539851)

Last update: 2021/09/25 05:17

