

rechnung_nichtinvertierender_verstaerker_eingangswiderstand

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

$\$ \backslash \text{quad} \$$	$\$ R_{\text{I}}^0 = \frac{U_{\text{I}}}{I_{\text{p}}} \$$
$\$ \backslash \text{quad} \$$	$\$ \backslash \text{quad} \$$
$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$
$\$ \backslash \text{quad} \$$	$\$ R_{\text{I}}^0 = \frac{U_{\text{I}}}{\color{blue} I_{\text{p}}} \$$
$\$ \backslash \text{quad} \$$	with $\$ I_{\text{p}} \$$ from $\$ R_{\text{D}} = \frac{U_{\text{D}}}{I_{\text{p}}} \$$
$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$
$\$ \backslash \text{quad} \$$	$\$ R_{\text{I}}^0 = \frac{U_{\text{I}} \cdot \color{blue} R_{\text{D}}}{\color{blue} U_{\text{D}}} \$$
$\$ \backslash \text{quad} \$$	$\$ \backslash \text{quad} \$$
$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$
$\$ \backslash \text{quad} \$$	$\$ R_{\text{I}}^0 = \frac{U_{\text{I}} \cdot R_{\text{D}}}{\color{blue} U_{\text{D}}} \$$
$\$ \backslash \text{quad} \$$	with $\$ U_{\text{D}} = \frac{U_{\text{O}}}{A_{\text{D}}} \$$
$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$
$\$ \backslash \text{quad} \$$	$\$ R_{\text{I}}^0 = \frac{U_{\text{I}} \cdot R_{\text{D}} \cdot \color{blue} A_{\text{D}}}{\color{blue} U_{\text{O}}} \$$
$\$ \backslash \text{quad} \$$	reshaped
$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$
$\$ \backslash \text{quad} \$$	$\$ R_{\text{I}}^0 = \frac{U_{\text{I}}}{U_{\text{O}}} \cdot R_{\text{D}} \cdot A_{\text{D}} \$$
$\$ \backslash \text{quad} \$$	$\$ \backslash \text{quad} \$$
$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$
$\$ \backslash \text{quad} \$$	$\$ R_{\text{I}}^0 = \color{blue} \frac{U_{\text{I}}}{U_{\text{O}}} \cdot R_{\text{D}} \cdot A_{\text{D}} \$$
$\$ \backslash \text{quad} \$$	with $\$ A_{\text{V}} = \frac{U_{\text{O}}}{U_{\text{I}}} = \frac{R_2}{R_1 + R_2} \$$
$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$
$\$ \backslash \text{quad} \$$	$\$ R_{\text{I}}^0 = \frac{1}{A_{\text{V}}} \cdot R_{\text{D}} \cdot A_{\text{D}} \$$
$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$
$\$ \backslash \text{quad} \$$	$\$ R_{\text{I}}^0 = \frac{A_{\text{D}}}{A_{\text{V}}} \cdot R_{\text{D}} \$$
$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: https://mexle.te.hs-heilbronn.de/circuit_design/rechnung_nichtinvertierender_verstaerker_eingangswiderstand

Last update: 2025/12/13 21:55

