

# rechnung\_spannungsfolger

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

### I. Analysis of the Currents

aus (2+3)	$I_p = I_m = 0$	Therefore, $I_p$ and $I_m$ are defined
aus (3) und (5)	$I_o = I_m = 0$	By this, $I_o$ is defined

### II. Analysis of the Voltage Amplification

aus (0)	$A_V = \frac{U_A}{U_E}$	
	$A_V = \frac{U_A}{U_E}$	mit (4)
	$A_V = \frac{U_A}{U_A + U_D}$	
	$A_V = \frac{U_A}{U_A} \cdot \frac{U_A + U_D}{U_A + U_D}$	with (1)
	$A_V = \frac{A_D \cdot U_D}{A_D \cdot U_D + U_D}$	
	$A_V = \frac{A_D \cdot U_D}{A_D \cdot U_D + U_D}$	
	$A_V = \frac{A_D \cdot U_D}{A_D \cdot U_D + U_D}$	Expand with $\frac{1}{A_D \cdot U_D}$
	$A_V = \frac{A_D \cdot U_D}{A_D \cdot U_D + U_D} \cdot \frac{1}{A_D \cdot U_D}$	
	$A_V = \frac{1}{1 + \frac{1}{A_D}}$	
	$A_V = \frac{1}{1 + \frac{1}{A_D}}$	with $\frac{1}{A_D} \rightarrow \infty$
	$A_V = \frac{1}{1 + 0}$	
	$A_V = \frac{1}{1} = 1$	

From:  
<https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:  
[https://mexle.te.hs-heilbronn.de/circuit\\_design/rechnung\\_spannungsfolger?rev=1636906127](https://mexle.te.hs-heilbronn.de/circuit_design/rechnung_spannungsfolger?rev=1636906127)

Last update: 2021/11/14 17:08

