

rechnung_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

$U_A = f(U_E)$	mit III.	
$\frac{d}{dt} U_A = \frac{d}{dt} f(U_E)$	$\frac{d}{dt} U_A = \frac{d}{dt} f(U_E)$	$\frac{d}{dt} U_A = \frac{d}{dt} f(U_E)$
$U_A = \frac{1}{C} U_D - U_C$	mit II. und I.	$U_D = \frac{1}{C} U_A + U_C$
$\frac{d}{dt} U_A = \frac{d}{dt} (\frac{1}{C} U_D - U_C)$	$\frac{d}{dt} U_A = \frac{d}{dt} (\frac{1}{C} U_D - U_C)$	$\frac{d}{dt} U_A = \frac{d}{dt} (\frac{1}{C} U_D - U_C)$
$U_A = 0 - \frac{1}{C} U_C$	mit V.	$U_C = -C U_A$
$\frac{d}{dt} U_A = \frac{d}{dt} (-\frac{1}{C} U_C)$	$\frac{d}{dt} U_A = \frac{d}{dt} (-\frac{1}{C} U_C)$	$\frac{d}{dt} U_A = \frac{d}{dt} (-\frac{1}{C} U_C)$
$U_A = -\frac{1}{C} \int I_C dt + Q_0(t_0)$	mit IV.	$I_C = I_R$
$\frac{d}{dt} U_A = -\frac{1}{C} I_C$	$\frac{d}{dt} U_A = -\frac{1}{C} I_C$	$\frac{d}{dt} U_A = -\frac{1}{C} I_C$
$U_A = -\frac{1}{C} \int I_R dt + Q_0(t_0)$	Ausklammern	
$\frac{d}{dt} U_A = -\frac{1}{C} I_R$	$\frac{d}{dt} U_A = -\frac{1}{C} I_R$	$\frac{d}{dt} U_A = -\frac{1}{C} I_R$
$U_A = -\frac{1}{C} \int I_R dt + U_{A0}$	Integrationskonstante betrachten	$U_{A0} = U_A(t_0) = -\frac{1}{C} \int I_R dt + U_{A0}$
$\frac{d}{dt} U_A = -\frac{1}{C} I_R$	$\frac{d}{dt} U_A = -\frac{1}{C} I_R$	$\frac{d}{dt} U_A = -\frac{1}{C} I_R$
$U_A = -\frac{1}{C} \int I_R dt + U_{A0}$	mit VI. und II.	$I_R = U_R / R = U_E / R$
$\frac{d}{dt} U_A = -\frac{1}{C} \frac{U_E}{R}$	$\frac{d}{dt} U_A = -\frac{1}{C} \frac{U_E}{R}$	$\frac{d}{dt} U_A = -\frac{1}{C} \frac{U_E}{R}$
$U_A = -\frac{1}{C} \int \frac{U_E}{R} dt + U_{A0}$	Konstante vorziehen	
$\frac{d}{dt} U_A = -\frac{1}{C} \frac{U_E}{R}$	$\frac{d}{dt} U_A = -\frac{1}{C} \frac{U_E}{R}$	$\frac{d}{dt} U_A = -\frac{1}{C} \frac{U_E}{R}$
$U_A = -\frac{1}{C} \int \frac{U_E}{R} dt + U_{A0}$	Zeitkonstante $\tau = R \cdot C$ einfügen	
$\frac{d}{dt} U_A = -\frac{1}{\tau} U_E$	$\frac{d}{dt} U_A = -\frac{1}{\tau} U_E$	$\frac{d}{dt} U_A = -\frac{1}{\tau} U_E$
$U_A = -\int \frac{U_E}{\tau} dt + U_{A0}$		
$\frac{d}{dt} U_A = -\frac{U_E}{\tau}$	$\frac{d}{dt} U_A = -\frac{U_E}{\tau}$	$\frac{d}{dt} U_A = -\frac{U_E}{\tau}$

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: https://mexle.te.hs-heilbronn.de/circuit_design/rechnung_umkehrintegrator?rev=1641767933

Last update: 2022/01/09 23:38

