

rechnung_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

$U_A = f(U_E)$		
with III.		
$U_A = \color{blue}{-U_D} - U_C$		
with II. and I.	$\color{blue}{U_D} = \frac{1}{A_D} \cdot U_A \overset{A_D}{\rightarrow} \infty$	
$U_A = 0 - \color{blue}{U_C}$		
with V.	$\color{blue}{U_C} = \frac{1}{C} \cdot (\int_{t_0}^{t_1} I_C \, dt + Q_0(t_0))$	
$U_A = -\frac{1}{C} \cdot (\int_{t_0}^{t_1} I_C \, dt + Q_0(t_0))$		
with IV.	$\color{blue}{I_C} = I_R$	
$U_A = \color{blue}{-\frac{1}{C} \cdot (\int_{t_0}^{t_1} I_R \, dt + Q_0(t_0))}$		
Factor out		
$U_A = -\frac{1}{C} \cdot (\int_{t_0}^{t_1} I_R \, dt - \color{blue}{\frac{Q_0(t_0)}{C}})$		
consider the integration constant	$\color{blue}{\frac{Q_0(t_0)}{C}} = U_C(t_0) = -U_{A0}$	
$U_A = -\frac{1}{C} \cdot (\int_{t_0}^{t_1} I_R \, dt + U_{A0})$		
with VI. and II.	$\color{blue}{I_R} = \frac{U_R}{R} = \frac{U_E}{R}$	
$U_A = -\frac{1}{C} \cdot (\int_{t_0}^{t_1} \frac{U_E}{R} \, dt + U_{A0})$		
move constant ahead		
$U_A = -\frac{1}{R \cdot C} \cdot (\int_{t_0}^{t_1} U_E \, dt + U_{A0})$		
insert time constant		
$\tau = R \cdot C$		
$U_A = -\frac{1}{\tau} \cdot (\int_{t_0}^{t_1} U_E \, dt + U_{A0})$		

From: <https://mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link: https://mexle.te.hs-heilbronn.de/circuit_design/rechnung_umkehrintegrator?rev=1641768811

Last update: **2022/01/09 23:53**

