

# rechnung\_umkehrintegrator

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

	$U_A = f(U_E)$
	with III.
$U_A = \frac{1}{A_D} U_C$	
with II. and I.: $\frac{1}{A_D} U_C = \frac{1}{A_D} U_C \overset{A_D \rightarrow}{\infty} \rightarrow 0$	
$U_A = 0 - U_C$	
with V.: $U_C = \frac{1}{C} \int_{t_0}^{t_1} I_C dt + Q_0(t_0)$	
$U_A = -\frac{1}{C} \int_{t_0}^{t_1} I_C dt + Q_0(t_0)$	
with IV.: $I_C = I_R$	
$U_A = -\frac{1}{C} \int_{t_0}^{t_1} I_R dt + Q_0(t_0)$	
Factor out	
$U_A = -\frac{1}{C} \int_{t_0}^{t_1} I_R dt - \frac{Q_0(t_0)}{C}$	
consider the integration constant: $\frac{Q_0(t_0)}{C} = U_C(t_0) = -U_{A0}$	
$U_A = -\frac{1}{C} \int_{t_0}^{t_1} I_R dt + U_{A0}$	
with VI. and II.: $I_R = \frac{U_R}{R} = \frac{U_E}{R}$	
$U_A = -\frac{1}{C} \int_{t_0}^{t_1} \frac{1}{R} U_E dt + U_{A0}$	
move constant ahead	
$U_A = -\frac{1}{R \cdot C} \int_{t_0}^{t_1} U_E dt + U_{A0}$	
insert time constant $\tau = R \cdot C$	
$U_A = -\frac{1}{\tau} \int_{t_0}^{t_1} U_E dt + U_{A0}$	

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: [https://mexle.te.hs-heilbronn.de/circuit\\_design/rechnung\\_umkehrintegrator?rev=1641769142](https://mexle.te.hs-heilbronn.de/circuit_design/rechnung_umkehrintegrator?rev=1641769142)

Last update: 2022/01/09 23:59

