

# task\_0j7accfimmemytq9\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E4 Cylindrical Coil (written test, approx. 6 % of a 120-minute written test, SS2021)	2
---	---

magnetostatic, flux density, magnetic field strength, coil, flux, exam ee2 SS2021

### Exercise E4 Cylindrical Coil

(written test, approx. 6 % of a 120-minute written test, SS2021)

A) The magnetic flux (2 points) information is given:

Result

- Length  $l = 30 \text{ cm}$ ,

Path Winding diameter  $d = 390 \text{ mm}$ ,

- Number of windings  $N = 240$ ,

Current  $I = 0.5 \text{ A}$  in the conductor  $I = 500 \text{ mA}$ ,

- Material inside: Air

$\mu_0 = 4\pi \cdot 10^{-7} \text{ Vs/Am}$

The magnetic field strength  $B = \mu_0 \mu_r H$ :

The proportion of the magnetic voltage outside the coil can be neglected. Determine the following for the inside of the coil.

a) Determine the magnetic field strength  $H$  and the magnetic flux  $\Phi$  (2 points)

Putting in the numbers:  $H = \frac{N \cdot I}{l} = \frac{240 \cdot 0.5 \text{ A}}{0.3 \text{ m}} = 400 \text{ A/m}$

$\Phi = B \cdot A = \mu_0 \mu_r H \cdot A = 4\pi \cdot 10^{-7} \text{ Vs/Am} \cdot 400 \text{ A/m} \cdot \pi \cdot \left(\frac{0.39 \text{ m}}{2}\right)^2 = 0.0005026 \text{ Vs}$

Path

Therefore:  $\Phi = B \cdot \pi \cdot \left(\frac{d}{2}\right)^2$

$\Phi = 0.0005026 \text{ Vs}$

Putting in the numbers:  $\Phi = 0.0005026 \text{ Vs}$

$H = \frac{N \cdot I}{l} = \frac{240 \cdot 0.5 \text{ A}}{0.3 \text{ m}} = 400 \text{ A/m}$

Putting in the numbers:  $H = \frac{240 \cdot 0.5 \text{ A}}{0.3 \text{ m}} = 400 \text{ A/m}$

From:

<https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:

[https://mexle.te.hs-heilbronn.de/electrical\\_engineering\\_and\\_electronics/task\\_0j7accfimmemytq9\\_with\\_calculation](https://mexle.te.hs-heilbronn.de/electrical_engineering_and_electronics/task_0j7accfimmemytq9_with_calculation)

Last update: 2024/07/03 08:55

