

task_9xy69axg3gi3nr26_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E13 Complex series circuit (written test, approx. 8 % of a 120-minute written test, SS2021) 2

complex voltage divider, exam ee2 SS2021

Exercise E13 Complex series circuit (written test, approx. 8 % of a 120-minute written test, SS2021)

A) Determine the absolute value of the result \underline{Z}_C in Ω once the series circuit is closed. Pay attention to the correct dimensioning.

a) Determine the complex impedance \underline{Z}_C .

Result

$$\underline{Z}_C = -j \cdot 804 \, \Omega$$

Path

The complex impedance \underline{Z}_C is given as

$$\underline{Z}_C = \frac{1}{j \cdot 2\pi \cdot f \cdot C} = \frac{-j}{2\pi \cdot 40 \cdot 10^3 \, \text{Hz} \cdot 4.95 \cdot 10^{-9} \, \text{F}} = -j \cdot 803.81... \, \Omega$$

Based on the diagram: $|\underline{Z}| = 828 \, \Omega$

From:
<https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:
https://mexle.te.hs-heilbronn.de/electrical_engineering_and_electronics/task_9xy69axg3gi3nr26_with_calculation

Last update: 2024/07/04 00:46

