

# task\_ddjurcpk494go2q1\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E6 Fields of an coax Cable (written test, approx. 12 % of a 120-minute written test, SS2024) ..... 2

electric field, magnetic field, exam ee2 SS2024

Exercise E6 Fields of an coax Cable (written test, approx. 12 % of a 120-minute written test, SS2024)

2. On the graph of the magnitude of the electric field  $E(r)$  with the radius  $r$  of the coax cable (dia.  $4.0\text{ mm}$ ) shows the cross-section (0.5 mm) of the inner conductor (0.6 mm) in the center diagram. Use appropriate dimensions and labels for the diagram.

Path

Inner conductor:  $+3.3\text{ mA}$ ,  $+10\text{ nC}$  (current into the plane of the diagram)

Outer conductor:  $-3.3\text{ mA}$ ,  $0\text{ nC}$  (current out of the plane of diagram)

- for  $(0.1\text{ mm} | 0)$ :  $E_{\text{in}} = 328\text{ V/m}$
- for  $(0.55\text{ mm} | 0)$ :  $E_{\text{out}} = 0.985\text{ V/m}$

The magnitude of the electric displacement field  $D$  can be calculated by:  $\int D \cdot dA = Q_{\text{enc}}$ .

In general, the  $E$ -field is proportional to  $1/r$  for the situation between both conductors (here for simplicity without the round endings). Here, the enclosing area is the surface of a cylindrical shape (here for simplicity without the round endings). So, the surface area of the cylinder is  $A = 2\pi r \cdot l$ . This leads to:  $D(r) = \frac{Q_{\text{enc}}}{2\pi r \cdot l}$ .

This is proportional to the area within this radius. Therefore, the formula  $H = \frac{I_{\text{enc}}}{2\pi r}$  gets  $H(x) = \frac{I_{\text{enc}}}{2\pi \cdot (0.1\text{ mm})}$ . This leads to a formula proportional to  $x$ .

For  $x$  within the outer conductor one also gets a linear proportionality with a different slope:  $H(x) = \frac{I_{\text{enc}}}{2\pi \cdot r_{\text{in}}}$  and  $H(x) = \frac{I_{\text{enc}}}{2\pi \cdot r_{\text{out}}}$ .

Hint: For the direction, one has to consider the sign of the enclosed charge. By this, we see that the  $D$ -field is positive. But here, again only the magnitude was questioned!

.. What is the magnitude of the magnetic field strength  $H$  at  $(0.1\text{ mm} | 0)$  and  $(0.55\text{ mm} | 0)$ ?

Path

The magnitude of the magnetic field strength  $H$  can be calculated by:  $H = \frac{I}{2 \pi \cdot r}$

So, we get for  $H_{\text{i}}$  at  $r_{\text{i}} = 0.1 \text{ mm}$ , and  $H_{\text{o}}$  at  $r_{\text{o}} = 0.55 \text{ mm}$ :

$$H_{\text{i}} = \frac{I}{2 \pi \cdot r_{\text{i}}} = \frac{+3.3 \text{ A}}{2 \pi \cdot 0.1 \cdot 10^{-3} \text{ m}} \quad H_{\text{o}} = \frac{I}{2 \pi \cdot r_{\text{o}}} = \frac{+3.3 \text{ A}}{2 \pi \cdot 0.55 \cdot 10^{-3} \text{ m}}$$

Hint: For the direction, one has to consider the right-hand rule. By this, we see that the  $H$ -field on the right side points downwards.

Therefore, the sign of the  $H$ -field is negative.

But here, only the magnitude was questioned!

From:

<https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:

[https://mexle.te.hs-heilbronn.de/electrical\\_engineering\\_and\\_electronics/task\\_ddjurcpgk494go2q1\\_with\\_calculation](https://mexle.te.hs-heilbronn.de/electrical_engineering_and_electronics/task_ddjurcpgk494go2q1_with_calculation)

Last update: 2026/01/23 10:10

