

# task\_jti0uzudcmg4u22t\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E5 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022) .....	2
---	---

complex impedance, exam ee1 WS2022

Exercise E5 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the phasor voltage  $\underline{U}$  and the current  $\underline{I}$  in the circuit shown in the figure. The components ( $R$  and  $X_L$ ) shall be given.

After analysis, the full width dimensioned phasor voltage  $\underline{U}$  and current  $\underline{I}$  in phasor notation shall be given.

Solution  
.. Calculation of physical values of the components.  
Solution  $R = 10 \Omega$ ,  $X_L = 20 \Omega$

Solution  
$$\underline{I} = \frac{\underline{U}}{\underline{Z}} \quad \underline{U} = 50 \angle 0^\circ \text{ V}$$
  
The current and voltage across the inductor is  $\underline{U}_L = j\omega L \underline{I}$   
resulting in  $\underline{U}_L = j\omega L \frac{\underline{U}}{\underline{Z}}$   
The voltage across the capacitor is  $\underline{U}_C = \frac{\underline{U}}{\underline{Z}} \cdot \frac{1}{j\omega C}$   
impedance  $\underline{Z} = R + j\omega L + \frac{1}{j\omega C}$   
$$\underline{Z} = 10 + j20 - j10 = 10 + j10 \Omega$$
  
$$\underline{I} = \frac{50 \angle 0^\circ}{10 + j10} = \frac{50}{\sqrt{200}} \angle -45^\circ = 3.54 \angle -45^\circ \text{ A}$$
  
With the complex part comes the complex value  $\underline{U}_L = j\omega L \underline{I}$   
$$\underline{U}_L = j20 \cdot 3.54 \angle -45^\circ = 70.8 \angle 45^\circ \text{ V}$$
  
The phase  $\varphi$  can be calculated as  $\varphi = \arctan\left(\frac{\text{Im}(\underline{U}_L)}{\text{Re}(\underline{U}_L)}\right) = \arctan\left(\frac{50}{50}\right) = 45^\circ$

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki  
Permanent link: [https://mexle.te.hs-heilbronn.de/electrical\\_engineering\\_and\\_electronics/task\\_jti0uzudcmg4u22t\\_with\\_calculation](https://mexle.te.hs-heilbronn.de/electrical_engineering_and_electronics/task_jti0uzudcmg4u22t_with_calculation)  
Last update: 2023/04/02 00:27

