

task_jti0uzudcmg4u22t_with_calculation

Student Group

| First Name | Surname | Matrikel Nr. |
|------------|---------|--------------|
| | | |
| | | |
| | | |

Table of Contents

Exercise E2 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022) 2

complex impedance, exam ee1 WS2022

Exercise E2 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the phasor voltage \underline{U} and the phasor current \underline{I} in the circuit shown in the figure. The components (R and X_L) shall be given.

After analysis, the full width dimensioned phasor voltage \underline{U} and the phasor current \underline{I} in phase (in Z) are $\underline{U} = \sqrt{2} \cdot 10 \cdot \cos(\omega t + 45^\circ)$ V and $\underline{I} = \sqrt{2} \cdot 1 \cdot \cos(\omega t + 5^\circ)$ A.

Solution
.. Calculation of physical values of the components.
Solution $R = 10 \Omega$, $X_L = 20 \Omega$

Solution

$\underline{I} = \frac{\underline{U}}{Z} = \frac{10 \angle 45^\circ}{10 + j20} = 0.447 \angle -63.4^\circ$ A

The current and voltage across the inductor are $\underline{U}_L = j\omega L \underline{I} = j20 \cdot 0.447 \angle -63.4^\circ = 8.94 \angle -23.4^\circ$ V

resulting in $u_L(t) = 8.94 \sqrt{2} \cos(\omega t - 23.4^\circ)$ V

The voltage across the resistor is $\underline{U}_R = R \underline{I} = 10 \cdot 0.447 \angle -63.4^\circ = 4.47 \angle -63.4^\circ$ V

impedance $Z = R + jX_L = 10 + j20 \Omega$

With the complex part comes the phase angle $\varphi = \arctan\left(\frac{X_L}{R}\right) = \arctan\left(\frac{20}{10}\right) = 63.4^\circ$

The phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(Z)}{\text{Re}(Z)}\right) = \arctan\left(\frac{20}{10}\right) = 63.4^\circ$

The phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(Z)}{\text{Re}(Z)}\right) = \arctan\left(\frac{20}{10}\right) = 63.4^\circ$

The phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(Z)}{\text{Re}(Z)}\right) = \arctan\left(\frac{20}{10}\right) = 63.4^\circ$

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: https://mexle.te.hs-heilbronn.de/ee1/task_jti0uzudcmg4u22t_with_calculation

Last update: 2023/04/02 00:27

