

# task\_0j7accfimmemytq9\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E1 Cylindrical Coil (written test, approx. 6 % of a 120-minute written test, SS2021)	2
---	---

magnetostatic, flux density, magnetic field strength, coil, flux, exam ee2 SS2021

### Exercise E1 Cylindrical Coil (written test, approx. 6 % of a 120-minute written test, SS2021)

A) The magnetic flux (2 points) information is given:

Result

- Length  $l = 30 \text{ cm}$ ,

Path Winding diameter  $d = 390 \text{ mm}$ ,

- Number of windings  $N = 240$ ,
- Current in the conductor  $I = 500 \text{ mA}$ .

• Material inside: Air

$$\mu_0 = 4\pi \cdot 10^{-7} \frac{\text{Vs}}{\text{Am}}$$

The magnetic field strength  $B = \mu_0 \mu_r H$ :

The proportion of the magnetic voltage outside the coil can be neglected. Determine the following for the inside of the coil:

a) the magnetic field strength (2 points)

$$B = \mu_0 \cdot N \cdot I \cdot \frac{1}{l} = 4\pi \cdot 10^{-7} \frac{\text{Vs}}{\text{Am}} \cdot 240 \cdot 0.5 \frac{\text{A}}{\text{m}} = 0.0005026... \frac{\text{Vs}}{\text{m}^2}$$

$$A = \pi r^2 = \pi \left( \frac{d}{2} \right)^2$$

path

$$\Phi = B \cdot A = 0.0005026... \frac{\text{Vs}}{\text{m}^2} \cdot \pi \left( \frac{0.39 \text{ m}}{2} \right)^2 = 0.00006004 \text{ Vs}$$

$$H = \frac{N \cdot I}{l} = \frac{240 \cdot 0.5 \text{ A}}{0.3 \text{ m}} = 400 \frac{\text{A}}{\text{m}}$$

$$B = \mu_0 \cdot H = 4\pi \cdot 10^{-7} \frac{\text{Vs}}{\text{Am}} \cdot 400 \frac{\text{A}}{\text{m}} = 0.0005026... \frac{\text{Vs}}{\text{m}^2}$$

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: [https://mexle.te.hs-heilbronn.de/ee2/task\\_0j7accfimmemytq9\\_with\\_calculation?rev=1719960177](https://mexle.te.hs-heilbronn.de/ee2/task_0j7accfimmemytq9_with_calculation?rev=1719960177)

Last update: 2024/07/03 00:42

