

# 7 Networks at variable frequency

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

<b>7. Networks at variable frequency</b> .....	2
Introduction .....	2
Targets .....	2
<b>7.1 From Two-Terminal Network to Four-Terminal Network</b> .....	2
Reminder: .....	3
<b>7.2 RL Series Circuit</b> .....	4
7.2.1 RL High Pass .....	5
Reminder: .....	9
7.2.2 RL Low Pass .....	18
<b>7.3 RC Series Circuit</b> .....	22
7.3.1 RC High Pass .....	22
7.3.2 RC Low Pass .....	26

# 7. Networks at variable frequency

Further content can be found at this [Tutorial](#) or that [Tutorial](#)

## Introduction

At the previous chapters it was explained how the “influence of a sinusoidal current flow” of capacitor and inductors look like. To describe this, the impedance was introduced. This can be understood as a complex resistance for sinusoidal excitation.

It applies to the capacitor:

$$\begin{aligned} \underline{U}_C &= \frac{1}{j\omega C} \cdot \underline{I}_C \quad \rightarrow \\ \underline{Z}_C &= \frac{1}{j\omega C} \end{aligned}$$

and for the inductance

$$\begin{aligned} \underline{U}_L &= j\omega L \cdot \underline{I}_L \quad \rightarrow \\ \underline{Z}_L &= j\omega L \end{aligned}$$

Complex impedances can be dealt with in much the same way as ohmic resistances in Electrical Engineering 1 (see: [simple DC Circuits](#), [linear Sources and two-terminal network](#), [Analysis of DC Networks](#)). In these transformations, the fraction  $j\omega$  is preserved. Circuits with impedances such as inductors and capacitors will show a frequency dependence accordingly.


### Targets

After this lesson, you should:

1. know that ...
2. know that ... is formed.
3. be able to ... can ...

## 7.1 From Two-Terminal Network to Four-Terminal Network

Fig. 1: Two-Terminal Network to Four-Terminal Network



Until now, components such as resistors, capacitors and inductors have been understood as two-terminal. This is also obvious, since there are only two connections. In the following however circuits are considered, which behave similar to a voltage divider: On one side a voltage  $U_1$  is applied, on the other side  $U_2$  is formed with it. This results in 4 terminals. The circuit can and will be considered as a four-terminal network in the following. However, the input and output values will be complex.

For a four-terminal network, the relation of “what goes out” (e.g.  $\underline{U}_2$  or  $\underline{U}_O$ ) to “what goes in” (e.g. voltage  $\underline{U}_1$  or  $\underline{U}_I$ ) is important. Thus, the output and input variables ( $\underline{U}_O$ ) and ( $\underline{U}_I$ ) give the quotient:

$$\begin{aligned} \underline{A} &= \frac{\underline{U}_O}{\underline{U}_I} \quad \& \text{with} \quad ; \\ \underline{U}_O &= U_O \cdot e^{j \varphi_U} \quad \& \text{and} \quad ; \quad \underline{U}_I = U_I \cdot e^{j \varphi_U} \\ \underline{A} &= \frac{\underline{U}_O}{\underline{U}_I} \end{aligned}$$

$$\boxed{\underline{A}} = \frac{\underline{U}_O}{\underline{U}_I} = \frac{U_O}{U_I} \cdot e^{j \Delta \varphi_U}$$


**Reminder:**

- The complex-valued quotient  $\frac{\underline{U}_O}{\underline{U}_I}$  is called the **transfer function**.
- The frequency-dependent magnitude of the quotient  $A(\omega) = \frac{U_O}{U_I}$  is called **amplitude response** and the angular difference  $\Delta\varphi_u(\omega)$  is called **phase response**.

The frequency behaviour of the amplitude response and the frequency response is not only important in electrical engineering and electronics, but will also play a central role in control engineering.

## 7.2 RL Series Circuit

Fig. 2: RL-series



First, a series connection of a resistor  $R$  and an inductor  $L$  shall be considered (see figure 2). This structure is also called RL-element.

Here,  $\underline{U}_I = \underline{X}_I \cdot \underline{I}_I$  with  $\underline{X}_I = R + j\omega L$  and corresponding for  $\underline{U}_O$ : 
$$\underline{A} = \frac{\underline{U}_O}{\underline{U}_I} = \frac{\omega L}{\sqrt{R^2 + (\omega L)^2}} \cdot e^{j\left(\frac{\pi}{2} - \arctan \frac{\omega L}{R}\right)}$$

This results in the following for

- the amplitude response:  $A = \frac{\omega L}{\sqrt{R^2 + (\omega L)^2}}$  and
- the phase response:  $\Delta\varphi_u = \arctan \frac{R}{\omega L} = \frac{\pi}{2} - \arctan \frac{\omega L}{R}$

The main focus should first be on the amplitude response. Its frequency response can be derived from the equation in various ways.

1. Extreme frequency consideration of this RL circuit (in the equation and in the system)
2. Plotting amplitude and frequency response
3. Determination of prominent frequencies

These three points are now to be gone through.

## 7.2.1 RL High Pass

For the first step we investigate the limit consideration: We look at what happens, when the frequency  $\omega$  runs to the definition range limits, i.e.  $\omega \rightarrow 0$  and  $\omega \rightarrow \infty$ :

- For  $\omega \rightarrow 0$ ,  $A = \frac{\omega L}{\sqrt{R^2 + (\omega L)^2}} \rightarrow 0$  as the numerator approaches zero and the denominator remains greater than zero.
- For  $\omega \rightarrow \infty$ ,  $A \rightarrow 1$ , because in the root in the denominator  $(\omega L)^2$  becomes larger and larger in the ratio  $R^2$  to  $(\omega L)^2$ . So the root tends to  $\omega L$  and thus to the numerator.

It can thus be seen that:

- at small frequencies there is no voltage  $U_2$  at the output.
- at high frequencies  $A = \frac{U_O}{U_I} \rightarrow 1$ , so the voltage at the output is equal to the voltage at the input.

Result:

The RL element shown here therefore only allows large frequencies to pass (= pass through) and small ones are filtered out.

The circuit corresponds to a **high pass**.

This can also be derived from understanding the components:

- At small frequencies, the current in the coil and thus the magnetic field changes only slowly. So only a negligibly small reverse voltage is induced. The coil acts like a short circuit at low frequencies.
- At higher frequencies, the current generated by  $U_I$  through the coil changes faster, the induced voltage  $U_i = - dl / dt$  becomes large. As a result, the coil inhibits the current flow and a voltage drops across the coil.
- If the frequency becomes very high, only a negligible current flows through the coil - and hence through the resistor. The voltage drop at  $R$  thus approaches zero and the output voltage  $U_O$  tends towards  $U_I$ .

The transfer function can also be decomposed into amplitude response and frequency response. Often this plots are not given in with linear axis but:

- the amplitude response with a double logarithmic coordinate system and
- the phase response single logarithmic coordinate system.

By this, the course from low to high frequencies are easier to see. The following simulation in [figure 3](#) shows the amplitude response and frequency response in the lower left corner.

Fig. 3: RL high pass filter

For further consideration, the equation of the transfer function  $\underline{A} = \frac{\underline{U}_O}{\underline{U}_I}$  is to be rewritten so that it becomes independent of component values  $R$  and  $L$ .

This allows for a generalized representation. This representation is called **normalization**:

$$\underline{A} = \frac{\underline{U}_O}{\underline{U}_I} = \frac{\omega L}{\sqrt{R^2 + (\omega L)^2}} \cdot e^{j\left(\frac{\pi}{2} - \arctan \frac{\omega L}{R}\right)}$$


$$\underline{A}_{\text{norm}} = \frac{\omega L / R}{\sqrt{1 + (\omega L / R)^2}} \cdot e^{j\left(\frac{\pi}{2} - \arctan \frac{\omega L}{R}\right)}$$

$$= \frac{x}{\sqrt{1 + x^2}} \cdot e^{j\left(\frac{\pi}{2} - \arctan x\right)}$$

This equation behaves quite the same as the one considered so far.

figure 4 shows the two plots. On the x-axis,  $x = \omega L / R$  has been plotted as the normalization variable. This represents a weighted frequency.

Fig. 4: Amplitude and phase response of the RL high-pass filter



Here, too, the behavior determined in the limit value observation can be seen:

- at small frequencies  $\omega$  (corresponds to small  $x$ ), the amplitude response tends toward zero.
- At high frequencies, the ratio  $U_O / U_I = 1$  is established.

Interesting in the phase response is the point  $x = 1$ .

- Further to the left of this point (i.e. at smaller frequencies) a tenfold increase of the frequency  $\omega$  produces a tenfold increase of  $U_O / U_I$ .
- Further to the right of this point (i.e. at higher frequencies)  $U_O / U_I = 1$  remains.

So this point marks a limit. Far to the left, the ohmic resistance is significantly greater the amount of impedance of the coil:  $R \gg \omega L$ . far to the right is just the opposite.

The point  $x=1$  just marks the cut-off frequency.

It holds

$$\underline{A}_{\text{norm}} = \frac{x}{\sqrt{1 + x^2}} \cdot e^{j\left(\frac{\pi}{2} - \arctan x\right)} = \frac{U_O}{U_I} \cdot e^{j\varphi} \quad \left\{ \begin{array}{l} x \ll 1 \ \&$$





```

\qua
d\qu
ad
\frac
{U_O
}{U_
l}=\f
rac{
1}{\
sqrt{
2}}
&,
\varp
hi =
\frac
{\pi}
{4}
\,
\wide
hat{
=} \,
45°
\end
{arra
y}
\right
.
\end
{alig
n*}
<\W
RAP
>
<\W
RAP
>

```

**Rem  
inde  
r:**

- T  
h  
e  
c  
u  
t  
-  
o

**f**  
**f**  
**r**  
**e**  
**q**  
**u**  
**e**  
**n**  
**c**  
**y**  
\$  
f  
-  
c  
\$  
f  
o  
r  
h  
i  
g  
h  
-  
p  
a  
s  
s  
a  
n  
d  
l  
o  
w  
-  
p  
a  
s  
s  
f  
i  
l  
t  
e  
r  
s  
i  
s  
t  
h  
e  
r  
r

e  
q  
u  
e  
n  
c  
y  
a  
t  
w  
h  
i  
c  
h  
t  
h  
e  
o  
h  
m  
i  
c  
r  
e  
s  
i  
s  
t  
a  
n  
c  
e  
j  
u  
s  
t  
e  
q  
u  
a  
l  
s  
t  
h  
e  
v  
a  
l  
u  
e  
o

f  
t  
h  
e  
i  
m  
p  
e  
d  
a  
n  
c  
e

.

• The cut-off frequency separates a range in w

h  
i  
c  
h  
t  
h  
e  
f  
i  
l  
t  
e  
r  
a  
l  
l  
o  
w  
s  
s  
i  
g  
n  
a  
l  
s  
t  
h  
r  
o  
u  
g  
h  
f  
r  
o  
m  
o  
n  
e  
i  
n  
w  
h  
i  
c  
h  
t  
h  
e  
y  
a

r  
e  
s  
u  
p  
p  
r  
e  
s  
s  
e  
d  
(  
=  
b  
l  
o  
c  
k  
e  
d  
)  
.  
•  
A  
t  
t  
h  
e  
c  
u  
t  
-  
o  
f  
f  
r  
e  
q  
u  
e  
n  
c  
y  
,  
t  
h  
e  
p  
h  
a

s  
e  
\$  
\  
v  
a  
r  
p  
h  
i  
=  
4  
5  
°  
\$  
a  
n  
d  
t  
h  
e  
a  
m  
p  
l  
i  
t  
u  
d  
e  
\$  
A  
=  
\  
f  
r  
a  
c  
{  
1  
}  
{  
\  
s  
q  
r  
t  
{  
2  
}  
}

\$  
.  
•  
I  
n  
G  
e  
r  
m  
a  
n  
t  
h  
e  
c  
u  
t  
-  
o  
f  
F  
r  
e  
q  
u  
e  
n  
c  
y  
i  
s  
c  
a  
l  
l  
e  
d  
G  
r  
e  
n  
z  
f  
r  
e  
q  
u  
e  
n  
z  
\$

f  
—  
{  
G  
r  
}  
\$

These statements apply to single-stage passive filters, i.e. one RL or one RC element. Multi-stage filters are considered in circuit engineering.

The cut-off frequency



## **RL Low Pass s**

Fig.  
5:  
Circuit,  
point  
er  
diagram,  
and  
amplitude  
and  
phase  
response  
of RL  
low-  
pass  
filter

So  
far,  
only  
one  
variant  
of  
the  
RL  
element  
has  
been  
considered,  
namely  
the  
one  
where  
the  
output

volta  
ge  
\$\un  
derli  
ne{U  
}\_O\$  
is  
tapp  
ed at  
the  
induc  
tanc  
e.  
Here  
we  
will  
briefl  
y  
discu  
ss  
what  
happ  
ens  
when  
the  
two  
com  
pone  
nts  
are  
swap  
ped.

In  
this  
case,  
the  
norm  
alize  
d  
trans  
fer  
funct  
ion is  
give  
n by:

\begi  
n{ali  
gn\*}  
\und

```

erlin
e{A}
_{no
rm}
=
\frac
{1}{
\sqrt
{1 +
(\omega
ega
L /
R)^2
}}\c
dot
e^{-j
\omega
arcta
n
\frac
{\omega
ega
L}{R}
}
}
\end
{align*}

```

The cut-off frequency is again given by  $f_c = \frac{R}{2\pi L}$ .

Fig. 6: RL low pass

filter

## **7. 3 RC Se rie s Cir cui t**

### **7.3. 1 RC Hig h Pas s**

Fig.  
7:  
Circu  
it,  
point  
er  
diagr  
am,  
and  
ampl  
itude  
and  
phas  
e  
resp  
onse  
of  
the  
RC  
high-  
pass  
filter

Now  
a  
voltage  
divider  
is to be  
constructed  
by  
a  
resistor  
 $R$   
and  
a  
capacitor  
 $C$ .  
Quite  
similar  
to the  
previous  
chapters,  
the  
transfer  
function  
can  
also  
be  
determined  
here.

Here  
results  
as  
normalized  
transfer  
function

ion:

```

\begin{align*}
\underline{e^A}
_{\text{norm}}
=
\frac{\omega_{egaRC} \sqrt{1 + (\omega_{egaRC})^2}}{e^{\frac{\pi}{2} - j \arctan(\omega_{egaRC})}}
\end{align*}

```

In this case, the normalization variable  $x = \omega_{egaRC}$ . Again,



```

d
\right
arro
w
\qua
d
\box
ed{f
_{c}
=\fra
c{1}
{2
\pi\c
dot
RC}
}
\end
{alig
n*}

```

Fig.  
8: RC  
high  
pass  
filter

### 7.3. 2 RC Low Pas s

Fig.  
9:  
Circu  
it,  
point  
er  
diagr  
am,  
and  
ampl  
itude  
and  
phas  
e

response  
of RC  
low-pass  
filter

Again,  
the  
voltage at  
the  
impedance  
is  
to be  
used  
as  
the  
output  
voltage.  
This  
results in  
a  
low-pass  
filter.

Here  
results as  
normalized  
transfer  
function:

```
\begin{align*}
\underline{A}
_{no
```

```

rm}
=
\frac
{1}{
\sqrt
{1 +
(\omega
RC)^
2}}\
\cdot
e^{-j
\;
\arctan
n
(\omega
RC) }
\end
{align
n*}

```

Also,  
the  
cut-  
off  
frequ  
ency  
is  
give  
n by  
 $f_c$   
= $\frac{c}{2\pi RC}$

Fig.  
10:  
RC  
low  
pass  
filter

