

# task\_bln2sqhr55mlxrj3\_with\_calculation

## Student Group

| First Name | Surname | Matrikel Nr. |
|------------|---------|--------------|
|            |         |              |
|            |         |              |
|            |         |              |

## Table of Contents

|  |   |
|--|---|
| Exercise E1 Conversion: Vacuum Cleaner ..... | 2 |
|--|---|

[conversion](#), [power](#), [energy](#), [chapter1](#) 1

### Exercise E1 Conversion: Vacuum Cleaner

Your  $18\text{~}\{\text{V}\}$  vacuum cleaner is equipped with a  $4.0\text{~}\{\text{Ah}\}$  battery, it runs  $15\text{~}\{\text{min}\}$ .

How much electrical power is consumed by the motor during this time on average?

Solution:  $288\text{~}\{\text{W}\}$

$$\begin{aligned} W &= 18\text{~}\{\text{V}\} \cdot 4.0\text{~}\{\text{Ah}\} = 72\text{~}\{\text{Wh}\} \\ t &= 15\text{~}\{\text{min}\} = 0.25\text{~}\{\text{h}\} \\ P &= \frac{W}{t} = \frac{72\text{~}\{\text{Wh}\}}{0.25\text{~}\{\text{h}\}} = 288\text{~}\{\text{W}\} \end{aligned}$$

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: [https://mexle.te.hs-heilbronn.de/electrical\\_engineering\\_1/task\\_bln2sqhr55mlxrj3\\_with\\_calculation?rev=1680517559](https://mexle.te.hs-heilbronn.de/electrical_engineering_1/task_bln2sqhr55mlxrj3_with_calculation?rev=1680517559)

Last update: **2023/04/03 12:25**

