

task_jti0uzudcmg4u22t_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

complex impedance, exam WS2022

Exercise 1 : Analyzing complex Impedances

(written test, approx. 14% of a 60-minute written test, WS2022)

A circuit with an ideal voltage source ($U=50\text{ V}$, $f=330\text{ Hz}$) and two components (R and \underline{X}_1) shall be given.

After analysis, the following formula for the impedance was extracted:
$$\underline{Z} = \left(\frac{2}{3+4j} + 5j \right) \Omega$$

1. Calculate the physical values of the two components.

Solution

$$\begin{aligned} \underline{Z} &= \left(\frac{2}{3+4j} + 5j \right) \Omega \quad \&= \\ \frac{2}{3+4j} \cdot \frac{3-4j}{3-4j} + 5j & \quad \&= \\ \frac{2}{9+16} \cdot (3-4j) + 5j & \quad \&= \left(0.24 - 0.32j + 5j \right) \Omega \\ & \quad \&= 0.24 \Omega + j \cdot 4.68 \Omega \quad \&= R + j X_L \end{aligned}$$

With the complex part comes the physical value:
$$X_L = \omega L \quad L = \frac{X_L}{\omega} = \frac{4.68 \Omega}{2\pi \cdot 300 \text{ Hz}} \quad \&=$$

Final result

$$R = 0.24 \Omega \quad L = 2.26 \text{ mH}$$

2. Calculate the phase and absolute value of complex current \underline{I} through the circuit.

Solution

$$\begin{aligned} \underline{I} &= \frac{\underline{U}}{\underline{Z}} \quad \&= \left\{ \frac{50 \text{ V}}{0.24 \Omega + j \cdot 4.68 \Omega} \right\} \quad \&= \left\{ \frac{50 \text{ V}}{0.24 \Omega + j \cdot 4.68 \Omega} \right\} \cdot \left\{ \frac{0.24 \Omega - j \cdot 4.68 \Omega}{0.24 \Omega - j \cdot 4.68 \Omega} \right\} \\ & \quad \&= \left\{ \frac{50 \text{ V}}{(0.24 \Omega)^2 + (4.68 \Omega)^2} \right\} \cdot (0.24 \Omega - j \cdot 4.68 \Omega) \end{aligned}$$

The absolute value $|\underline{I}|$ can be calculated as:
$$|\underline{I}| = \frac{|\underline{U}|}{|\underline{Z}|} \quad \&= \left\{ \frac{50 \text{ V}}{0.24 \Omega + j \cdot 4.68 \Omega} \right\} \quad \&= \left\{ \frac{50 \text{ V}}{\sqrt{(0.24 \Omega)^2 + (4.68 \Omega)^2}} \right\}$$

The phase φ_i can be calculated as
$$\varphi_i = \arctan \left(\right)$$

