

# task\_rj0r6j4apumukrj6\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Excercise: Temperature-dependent resistance of a wire (written test, approx. 6% of a 60-minute written test, WS2022) ..... 2

resistivity, power

### Excercise: Temperature-dependent resistance of a wire (written test, approx. 6% of a 60-minute written test, WS2022)

A heating element made of a Nichrome wire with a round cross-section is used in an electric oven. Nichrome is a common Nickel Chromium alloy for heating elements. The Nichrome wire has a resistivity of  $1.10 \cdot 10^{-6} \text{ } \Omega \text{ m}$ . The heating element is  $3 \text{ m}$  long and has a diameter of  $3.57 \text{ mm}$ .

1. Calculate the resistance  $R$  of the heating element.

Solution

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad | \quad \text{with } A = r^2 \cdot \pi = \frac{1}{4} d^2 \cdot \pi \\ R &= \rho \cdot \frac{l}{\frac{1}{4} d^2 \cdot \pi} \quad || \quad R = 1.10 \cdot 10^{-6} \text{ } \Omega \text{ m} \cdot \frac{3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \end{aligned}$$

Final result

$$R = 0.33 \text{ } \Omega$$

2. The heating element is used to heat the oven to a temperature of  $180^\circ\text{C}$ . For this, a power dissipation (= heat flow) of  $P=40 \text{ W}$  is necessary. Calculate the current  $I$  needed to operate it.

Solution

$$P = U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}}$$

Final result

$$I = 11 \text{ A}$$

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: [https://mexle.te.hs-heilbronn.de/electrical\\_engineering\\_1/task\\_rj0r6j4apumukrj6\\_with\\_calculation?rev=1676150640](https://mexle.te.hs-heilbronn.de/electrical_engineering_1/task_rj0r6j4apumukrj6_with_calculation?rev=1676150640)

Last update: 2023/02/11 22:24

