

task_tb6pi8dgh0m2e2pw_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022) 2

Charging Capacitors, dc network analysis, pure resistor network simplification, delta wye transformation, exam ee1 WS2022


Exercise E1 Charging Capacitors

(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (with the real solution) is in the picture of $R_1 = 20 \Omega$ and $C = 100 \mu F$. The voltage across the capacitor is again 0 V at the moment $t_0 = 0 \text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2 = 1 \text{ ms}$ after closing the switch.

Solution
 To solve this, first create an equivalent linear voltage source from U , R_1 , and R_B .


Solution
 The delta voltage source is $U_s = U \cdot \frac{R_B}{R_1 + R_B} = 12 \text{ V} \cdot \frac{20 \Omega}{20 \Omega + 20 \Omega} = 6 \text{ V}$.
 The internal resistance is given by substituting the ideal voltage source is again short-circuiting R_1 .



The circuit contains a voltage source $U = 12 \text{ V}$, a switch S_1 , a resistor of $R_1 = 20 \Omega$ and a capacitor of $C = 100 \mu F$.
 The switch S_2 to an additional consumer R_2 will be considered to be open for the first asks. At the moment $t_0 = 0 \text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0) = 0 \text{ V}$.

.. First do not consider the light bulb - it is not connected to the RC circuit.
 Calculate the point of time t_1 when $u_c(t_1) = 0.5 \cdot U$.

Solution



An equivalent linear voltage source can be given with U_s , R_1 , and R_B as seen in yellow.
 Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = 1/2 \cdot U$. The internal resistance is given by substituting the ideal voltage source with its resistance ($= 0 \Omega$, short-circuit).

The following formula describes the current $i(t)$ in a circuit with a resistor R and a capacitor C in series, connected to a DC voltage source U_0 . The current $i(t)$ is given by:

The following formula describes the current $i(t)$ in a circuit with a resistor R and a capacitor C in series, connected to a DC voltage source U_0 . The current $i(t)$ is given by:

$$i(t) = \frac{U_0}{R} \left(1 - e^{-\frac{t}{\tau}} \right)$$

It has to be rearranged to $(1 - e^{-\frac{t}{\tau}}) \cdot R = U_0$

$$1 - e^{-\frac{t}{\tau}} = \frac{U_0}{R} \cdot C$$

$$e^{-\frac{t}{\tau}} = 1 - \frac{U_0}{R} \cdot C$$

$$-\frac{t}{\tau} = \ln\left(1 - \frac{U_0}{R} \cdot C\right)$$

$$t = -\tau \cdot \ln\left(1 - \frac{U_0}{R} \cdot C\right)$$

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: https://mexle.te.hs-heilbronn.de/electrical_engineering_1/task_tb6pi8dgh0m2e2pw_with_calculation?rev=1680388022

Last update: 2023/04/02 00:27

