

# Exam Winter Semester 2022

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E1 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022) .....	3
Exercise E1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) .....	6
Exercise E2 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022) .....	7
Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022) .....	7
Exercise E3 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) .....	10
Exercise E4 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) .....	10
Exercise E5 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022) .....	11
Exercise E6 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022) .....	12
Exercise E3 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022) .....	14
Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) .....	18
Exercise E5 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022) .....	19
Exercise E7 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022) .....	19
Exercise E6 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) .....	22
Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) .....	22
Exercise E4 Charging Capacitors (written test, approx. 16 % of a 60-minute written test,	

WS2022) ..... 23


Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute  
written test, WS2022) ..... 24

<DRAW hide>testtest</DRAW>

### Exercise E1 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)

The circuit in the following has to be simplified.  
Result

$$\begin{aligned} U_{\text{rs}} &= U_{\text{AB}} = 4.5 \text{ V} \\ R_{\text{i}} &= R_{\text{AB}} = 6 \Omega \end{aligned}$$




Calculated the internal resistance  $R_{\text{i}}$  and the source voltage  $U_{\text{rs}}$  of an equivalent linear voltage source on the connectors  $\text{A}$  and  $\text{B}$ . 
$$R_1=5.0 \Omega, \quad U_2=6.0 \text{ V}, \quad R_3= 10 \Omega, \quad I_4=4.2 \text{ A}, \quad R_5=10 \Omega, \quad R_6=7.5 \Omega, \quad R_7=15 \Omega$$
 Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of  $U_2$  and  $R_1$  can be transformed into a current source  $I_2 = \frac{U_2}{R_1}$  and  $R_1$ :



Now a lot of them can be combined. The resistors  $R_1$ ,  $R_3$ ,  $R_5$  are in parallel, like also  $I_2$  and  $I_4$ :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4$$

The resulting circuit can again be transformed:



Here, the  $U_{24}$  is calculated by  $I_{24}$  as the following:

$$U_{24} = I_{24} \cdot (R_6 || R_7)$$

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - I_4 \cdot R_1 || R_3 || R_5$$

On the right side of the last circuit, there is a voltage divider given by  $R_{135}$ ,  $R_6$ , and  $R_7$ .

Therefore the voltage between  $A$  and  $B$  is given as:

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - \left( \frac{U_2}{R_1} - I_4 \right) \cdot \left( R_1 || R_3 || R_5 \right)$$

For the internal resistance  $R_i$  the ideal voltage source is substituted by its resistance ( $=0\Omega$ , so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with  $R_1 || R_3 || R_5 = 5\Omega || 10\Omega || 10\Omega = 5\Omega || 5\Omega = 2.5\Omega$ :

$$U_{AB} = \left( \frac{6.0\text{V}}{5.0\Omega} \right) - 4.2\text{A} \cdot \left( \frac{15\Omega \cdot 2.5\Omega}{7.5\Omega + 15\Omega + 2.5\Omega} \right)$$

$$R_{AB} = 15\Omega || (7.5\Omega + 2.5\Omega)$$

**Exercise E1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)**

2. The diagram explains the effect of resistance on refrigeration systems. The circuit has a resistance of  $10\Omega$  at  $25^\circ\text{C}$  and  $25\text{W}$  of power.

Its temperature coefficients are:  $\alpha = 0.01 \text{ K}^{-1}$  and  $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$ .

**Result**  
The temperature inside the refrigeration system can reach down to  $-40^\circ\text{C}$ .

$$R_{25} = 10\Omega$$

The power of the resistor is  $P = U \cdot I$  and  $P = \frac{U^2}{R}$ . Therefore, a solution is to increase the resistance.

Therefore, with constant  $U$  and increasing  $R$  the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

$$\Delta T = T_{\text{end}} - T_{\text{start}}$$

$$R = 10\Omega \cdot \left( 1 + 0.01 \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \cdot 10^{-6} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2 \right)$$

### Exercise E2 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the complex impedance  $Z$  of the circuit shown in the figure through the components.  $R$  and  $X_L$  shall be given.

After analysis, the full bridge circuit can be simplified to a series circuit in phasor domain.  $Z = (2 + j4) \parallel (1 + j5) + 5$

Solution  
.. Calculate the physical values of the two components.  
Solution  $R = 2 \Omega$  and  $X_L = 4 \Omega$

Solution  
$$\underline{I} = \frac{\underline{U}}{\underline{Z}} \parallel = \frac{50}{(2 + j4) \parallel (1 + j5) + 5}$$
  
The voltage across the capacitor is  $U_C = I \cdot X_C = 50 \cdot \frac{1}{1 + j5}$   
resulting in  $I = \frac{U_C}{X_C} = \frac{50}{1 + j5}$   
Therefore, the component  $4.68 \Omega$  is in series with the same current  $I = 4.68 \Omega$   
impedance  $Z = \frac{U}{I} = \frac{50}{\frac{50}{1 + j5}} = 1 + j5$   
$$\underline{Z} = (2 + j4) \parallel (1 + j5) + 5 = \frac{(2 + j4)(1 + j5)}{(2 + j4) + (1 + j5)} + 5 = \frac{2 + j10 + j4 + j20}{3 + j9} + 5 = \frac{2 + j34}{3 + j9} + 5$$
  
The absolute value  $|Z| = \sqrt{0.24^2 + 4.68^2} = 4.70 \Omega$   
The phase  $\varphi = \arctan\left(\frac{4.68}{0.24}\right) = 87.06^\circ$   
With the complex part  $Z = 0.24 - j4.68$   
$$\varphi = \arctan\left(\frac{-4.68}{0.24}\right) = -87.06^\circ$$
  
The phase  $\varphi$  can be calculated as  $\varphi = \arctan\left(\frac{\text{Im}(Z)}{\text{Re}(Z)}\right) = \arctan\left(\frac{-4.68}{0.24}\right) = -87.06^\circ$


### Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)

2. Calculate the circuit impedance  $Z$  for a source  $u(t) = 3.0 \cdot \sin(2\pi \cdot 15 \cdot t)$  V. The circuit consists of a voltage source  $u(t) = 3.0 \cdot \sin(2\pi \cdot 15 \cdot t)$  V, a resistor  $R = 1 \Omega$ , an inductor  $L = 330 \mu\text{H}$ , and a capacitor  $C = 0.22 \mu\text{F}$ , all in series.

Solution  
Result  
.. Draw the circuit diagram of the given circuit and label all components, voltages, and currents.

$$Z = R + j\omega L - j\omega C = 1 + j2\pi \cdot 15 \cdot 330 \cdot 10^{-6} - j2\pi \cdot 15 \cdot 0.22 \cdot 10^{-6}$$
  
$$Z = 1 + j19.8 - j0.22$$
  
$$Z = 1 + j19.58$$
  
$$|Z| = \sqrt{1^2 + 19.58^2} = 19.61 \Omega$$
  
$$\varphi = \arctan\left(\frac{19.58}{1}\right) = 87.06^\circ$$





**Exercise E3 Impedances at different Frequencies**  
**(written test, approx. 18 % of a 60-minute written test, WS2022)**

2. A series circuit consists of a resistor with a resistance of  $R_1 = 1.00 \text{ k}\Omega$  and a capacitor with a capacitance of  $C_1 = 40 \text{ nF}$ . The voltage across the resistor is  $U_{R_1} = 100 \text{ V}$  at a frequency of  $f = 4 \text{ MHz}$ . Calculate the absolute value of the impedance of the capacitor  $Z_C$  and the total impedance  $Z_{\text{total}}$  of the circuit.

Solution

$Z_C = \frac{1}{j\omega C_1} = \frac{1}{j \cdot 2\pi \cdot 4 \cdot 10^6 \cdot 40 \cdot 10^{-9}} = -j0.995 \text{ k}\Omega$

$Z_{\text{total}} = R_1 + Z_C = 1.00 \text{ k}\Omega - j0.995 \text{ k}\Omega$

$|Z_{\text{total}}| = \sqrt{1.00^2 + 0.995^2} = 1.41 \text{ k}\Omega$

A series circuit means that the current is constant on every component.  
 The equivalent impedance for  $R$  and  $L$  combined is given by  $Z = R + j\omega L$   
 Parallel circuit means that the voltage is the same on  $R_2$  and  $C_2$   $U = U_{R_2} = U_{C_2}$   
 $\frac{1}{Z_{\text{parallel}}} = \frac{1}{R_2} + \frac{1}{j\omega C_2}$   
 $Z_{\text{parallel}} = \frac{R_2 \cdot j\omega C_2}{1 + R_2^2 \omega^2 C_2^2}$   
 $Z_{\text{parallel}} = \frac{4.7 \cdot j \cdot 2\pi \cdot 4 \cdot 10^6 \cdot 10^{-6}}{1 + (4.7 \cdot 2\pi \cdot 4 \cdot 10^6 \cdot 10^{-6})^2}$   
 $Z_{\text{parallel}} = \frac{j35.2}{1 + 35.2^2} = j0.995 \text{ k}\Omega$   
 Therefore, the resulting current of the parallel circuit is given as:  
 $I_{\text{parallel}} = \frac{U}{Z_{\text{parallel}}} = \frac{100 \text{ V}}{j0.995 \text{ k}\Omega} = -j0.01005 \text{ A} = -10.05 \text{ mA}$   
 This current is the same as the current through  $R_1$   $I_{R_1} = I_{\text{parallel}} = -10.05 \text{ mA}$   
 Back to the first formula:  $U_{R_1} = I_{R_1} \cdot R_1$   
 $100 \text{ V} = -10.05 \text{ mA} \cdot R_1$   
 $R_1 = \frac{100 \text{ V}}{-10.05 \text{ mA}} = -9.95 \text{ k}\Omega$

**Exercise E4 Resistance of a Wire by Resistivity**  
**(written test, approx. 6 % of a 60-minute written test, WS2022)**

2. For heating elements used to heat the oven at a temperature of  $180^\circ\text{C}$ , an electric power dissipation (= heat flow) of  $P = 40 \text{ W}$  is necessary.

Calculate the current  $I$  and the voltage  $U$  for heating elements.  
 The Nichrome wire has a resistivity of  $\rho = 1.10 \cdot 10^{-6} \text{ }\Omega \cdot \text{m}$ .  
 The heating element is  $l = 3 \text{ m}$  long and has a diameter of  $d = 3.57 \text{ mm}$ .  
 Calculate the resistance  $R$  of the heating element.

Solution

$P = U \cdot I = R \cdot I^2 \Rightarrow I = \sqrt{\frac{P}{R}}$

$$\sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \cdot \Omega}} \quad \text{align*}$$

$$\begin{aligned} R &= \rho \cdot l \cdot \frac{1}{A} \quad \& \quad | \quad \text{with } A = r^2 \cdot \pi = \\ &= \frac{1}{4} d^2 \cdot \pi \quad \& \quad R = \rho \cdot l \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ &= 1.10 \cdot 10^{-6} \cdot \Omega \cdot \text{m} \cdot \frac{4 \cdot 3 \cdot \text{m}}{(3.57 \cdot 10^{-3} \cdot \text{m})^2 \cdot \pi} \quad \& \quad \end{aligned}$$


**Exercise E5 Charging Capacitors**  
 (written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (with the light bulb) is a series of  $R_1$  and  $R_2$  and a capacitor  $C$  and a switch  $S_1$  and a switch  $S_2$ . The voltage across the capacitor is again  $0 \text{ V}$  at the moment  $t_0 = 0 \text{ s}$  when the switch  $S_1$  is closed. Calculate the voltage  $u_c(t_2)$  across the capacitor at  $t_2 = 1 \text{ ms}$  after closing the switch.

**Solution:** To solve this, first create an equivalent linear voltage source from  $U$ ,  $R_1$ , and  $R_2$ .

The ideal voltage source  $U$  is in series with  $R_1$  and  $R_2$ . The voltage  $u_c$  is independent of this series.


On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting  $S_2$ .



The circuit contains a voltage source  $U = 12 \text{ V}$ , a switch  $S_1$ , a resistor of  $R_1 = 20 \Omega$  and a capacitor of  $C = 100 \mu\text{F}$ . The switch  $S_2$  to an additional consumer  $R_2$  will be considered to be open for the first tasks. At the moment  $t_0 = 0 \text{ s}$  the switch  $S_1$  is closed, the voltage across the capacitor is  $u_c(t_0) = 0 \text{ V}$ .

... First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time  $t_1$  when  $u_c(t_1) = 0.5 \cdot U$ .

Solution





Since  $R_2=R_3$  and based on the equations for the transformation, the transformed  $R_Y$  is given as:


$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \, \Omega)^2}{3 \cdot 100 \, \Omega} = \frac{1}{3} \cdot 100 \, \Omega = 33.33 \, \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \, \Omega + (33.33 \, \Omega + 400 \, \Omega) \parallel (33.33 \, \Omega + 100 \, \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance  $R_{\text{eq}}$  between  $A$  and  $B$ .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_{-1}) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \Omega + 200 \Omega + 200 \Omega) \parallel (100 \Omega + 100 \Omega) \parallel R_{\text{eq}} = (500 \Omega) \parallel (200 \Omega) \parallel R_{\text{eq}} = \frac{500 \Omega \cdot 200 \Omega}{500 \Omega + 200 \Omega} \parallel$$

**Exercise E3 Equivalent linear Source  
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.  
Result

$$U_{\text{s}} = U_{\text{AB}} = 4.5 \text{ V} \quad R_{\text{i}} = R_{\text{AB}} = 6 \Omega$$




Calculated the internal resistance  $R_{\text{int}}$  and the source voltage  $U_{\text{oc}}$  of an equivalent linear voltage source on the connectors  $\text{A}$  and  $\text{B}$ .  $R_1=5.0 \text{ }\Omega$ ,  $U_2=6.0 \text{ V}$ ,  $R_3= 10 \text{ }\Omega$ ,  $I_4=4.2 \text{ A}$ ,  $R_5=10 \text{ }\Omega$ ,  $R_6=7.5 \text{ }\Omega$ ,  $R_7=15 \text{ }\Omega$  Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of  $U_2$  and  $R_1$  can be transformed into a current source  $I_2 = \frac{U_2}{R_1}$  and  $R_1$ :



Now a lot of them can be combined. The resistors  $R_1$ ,  $R_3$ ,  $R_5$  are in parallel, like also  $I_2$  and  $I_4$ : 
$$R_{135} = R_1 || R_3 || R_5$$
 
$$I_{24} = I_2 - I_4 = \frac{U_2}{R_1} - I_4$$
 The resulting circuit can again be transformed:



Here, the  $U_{24}$  is calculated by  $I_{24}$  as the following: 
$$U_{24}$$

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - I_4 \cdot R_1 || R_3 || R_5$$

On the right side of the last circuit, there is a voltage divider given by  $R_{135}$ ,  $R_6$ , and  $R_7$ .

Therefore the voltage between  $A$  and  $B$  is given as:

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - \left( \frac{U_2}{R_1} - I_4 \right) \cdot \left( R_1 || R_3 || R_5 \right)$$

For the internal resistance  $R_i$  the ideal voltage source is substituted by its resistance ( $=0 \Omega$ , so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with  $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$ :

$$U_{AB} = \left( \frac{6.0 \text{ V}}{5.0 \Omega} \right) - 4.2 \Omega \cdot \left( \frac{15 \Omega \cdot 2.5 \Omega}{7.5 \Omega + 15 \Omega + 2.5 \Omega} \right)$$

$$R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

**Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)**

2. A refrigerator is explained with the effect of resistance on the refrigeration system. The circuit has a resistance of  $15 \Omega$  and a voltage of  $6 \text{ V}$ . Your answer:

Its temperature coefficients are:  $\alpha = 0.01 \text{ K}^{-1}$  and  $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$

**Result**  
The temperature inside the refrigeration system can reach down to  $-40 \text{ }^\circ\text{C}$ .

$$R = 6.5 \text{ } \Omega$$

The power of the resistor is  $P = U \cdot I$  and  $Q = P \cdot t$ . Therefore, a solution is to use a heat pump.

Therefore, with constant  $U$  and increasing  $R$  the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

$$\Delta T = T_{\text{end}} - T_{\text{start}}$$

$$R = 10 \Omega \cdot \left( 1 + 0.01 \text{ K}^{-1} \cdot (-40 \text{ }^\circ\text{C} - 25 \text{ }^\circ\text{C}) + 71 \cdot 10^{-6} \text{ K}^{-2} \cdot (-40 \text{ }^\circ\text{C} - 25 \text{ }^\circ\text{C})^2 \right)$$

### Exercise E5 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the complex impedance  $Z$  of the circuit shown in the figure. The voltage  $u(t) = 3.0 \cdot \sin(2\pi \cdot 15 \cdot t)$  V and the current  $i(t) = 0.24 \cdot \sin(2\pi \cdot 15 \cdot t - \varphi)$  A shall be given.

After analysis, the following complex impedance  $Z$  shall be extracted and the phase angle  $\varphi$  in degrees shall be determined.  $Z = R + jX_L + jX_C + jX_M$  and  $\varphi = \dots$

Solution  
.. Calculate the physical values of the two components.  
Solution  $R = 10 \Omega$  and  $X_L = 2\pi \cdot 15 \cdot 0.2 = 1.88 \Omega$

Solution  
$$\underline{I} = \frac{\underline{U}}{\underline{Z}} \quad \|\ \&= \{ \{50 \text{ V}\} \over \{ \{4.68 - j0.24 \} \Omega \} \}$$
  
The voltage  $U = 50$  V is the effective value of the voltage  $u(t) = 3.0 \cdot \sin(2\pi \cdot 15 \cdot t)$  V. The resulting impedance  $Z = 4.68 - j0.24 \Omega$  is the complex impedance of the circuit. The real part  $R = 4.68 \Omega$  is the resistance and the imaginary part  $X_C = -0.24 \Omega$  is the capacitive reactance. The phase angle  $\varphi$  is the angle of the impedance  $Z$ .  
$$\varphi = \arctan\left(\frac{\text{Im}(Z)}{\text{Re}(Z)}\right) = \arctan\left(\frac{-0.24}{4.68}\right) = -2.9^\circ$$
  
The phase angle  $\varphi$  is  $-2.9^\circ$ .  
With the complex part  $Z = 4.68 - j0.24 \Omega$  and the voltage  $U = 50$  V, the current  $I$  is  $I = \frac{U}{Z} = \frac{50}{4.68 - j0.24} = 10.67 + j1.19$  A.  
The phase angle  $\varphi$  can be calculated as  $\varphi = \arctan\left(\frac{\text{Im}(I)}{\text{Re}(I)}\right) = \arctan\left(\frac{1.19}{10.67}\right) = 6.4^\circ$ .

### Exercise E7 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)


2. Calculate the complex impedance  $Z$  of the circuit shown in the figure. The voltage  $u(t) = 3.0 \cdot \sin(2\pi \cdot 15 \cdot t)$  V and the current  $i(t) = 0.24 \cdot \sin(2\pi \cdot 15 \cdot t - \varphi)$  A shall be given.

After analysis, the following complex impedance  $Z$  shall be extracted and the phase angle  $\varphi$  in degrees shall be determined.  $Z = R + jX_L + jX_C + jX_M$  and  $\varphi = \dots$

Solution  
Result  
.. Draw the circuit diagram of the given circuit.  
Solution  $Z = 10 + j1.88 - j0.24 = 10 + j1.64 \Omega$

Solution  
$$\underline{I} = \frac{\underline{U}}{\underline{Z}} \quad \|\ \&= \{ \{50 \text{ V}\} \over \{ \{10 + j1.64 \} \Omega \} \}$$
  
The voltage  $U = 50$  V is the effective value of the voltage  $u(t) = 3.0 \cdot \sin(2\pi \cdot 15 \cdot t)$  V. The resulting impedance  $Z = 10 + j1.64 \Omega$  is the complex impedance of the circuit. The real part  $R = 10 \Omega$  is the resistance and the imaginary part  $X_L = 1.64 \Omega$  is the inductive reactance. The phase angle  $\varphi$  is the angle of the impedance  $Z$ .  
$$\varphi = \arctan\left(\frac{\text{Im}(Z)}{\text{Re}(Z)}\right) = \arctan\left(\frac{1.64}{10}\right) = 9.2^\circ$$
  
The phase angle  $\varphi$  is  $9.2^\circ$ .  
With the complex part  $Z = 10 + j1.64 \Omega$  and the voltage  $U = 50$  V, the current  $I$  is  $I = \frac{U}{Z} = \frac{50}{10 + j1.64} = 4.82 - j0.78$  A.  
The phase angle  $\varphi$  can be calculated as  $\varphi = \arctan\left(\frac{\text{Im}(I)}{\text{Re}(I)}\right) = \arctan\left(\frac{-0.78}{4.82}\right) = -9.2^\circ$ .





**Exercise E6 Impedances at different Frequencies**  
**(written test, approx. 18 % of a 60-minute written test, WS2022)**

2. A series circuit consists of a resistor with a resistance of  $R_1 = 1.00 \text{ k}\Omega$ , a capacitor with a capacitance of  $C_1 = 40 \text{ nF}$ , and an inductor with an inductance of  $L_1 = 4.7 \text{ }\mu\text{H}$ . The circuit is connected to an AC voltage source with a voltage of  $U = 10 \text{ V}$  and a frequency of  $f = 4 \text{ MHz}$ . Calculate the absolute value of the impedance  $|Z|$  of the circuit.

Solution

$$|Z| = \sqrt{R_1^2 + (X_L - X_C)^2}$$

$$|Z| = \sqrt{(1.00 \text{ k}\Omega)^2 + (2\pi \cdot 4 \text{ MHz} \cdot 4.7 \text{ }\mu\text{H} - \frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}})^2}$$

A series circuit means that the current is constant on every component.  
 The equivalent impedance for  $R$  and  $L$  combined is given by  $Z = R + jX_L$   
 Parallel circuit means that the voltage is the same on  $R$  and  $C$   $Z = \frac{R \cdot X_C}{R + jX_C}$   
 $|Z| = \sqrt{R^2 + X_L^2}$  since  $X_L$  and  $X_C$  are perpendicular  
 $|Z| = \sqrt{R^2 + (X_L - X_C)^2}$  since  $X_L$  and  $X_C$  are perpendicular  
 $|Z| = \sqrt{R^2 + (2\pi \cdot f \cdot L - \frac{1}{2\pi \cdot f \cdot C})^2}$  (It has to, since  $R$  is perpendicular to  $X_L$  and  $X_C$  is perpendicular to  $X_L$ )  
 $|Z| = \sqrt{R^2 + (2\pi \cdot f \cdot L - \frac{1}{2\pi \cdot f \cdot C})^2} = \sqrt{R^2 + (2\pi \cdot 4 \text{ MHz} \cdot 4.7 \text{ }\mu\text{H} - \frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}})^2}$   
 Therefore, the resulting current of the parallel circuit is given as:  
 $I = \frac{U}{|Z|}$   
 $I = \frac{10 \text{ V}}{\sqrt{(1.00 \text{ k}\Omega)^2 + (2\pi \cdot 4 \text{ MHz} \cdot 4.7 \text{ }\mu\text{H} - \frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}})^2}}$   
 $I = \frac{10 \text{ V}}{\sqrt{(1.00 \text{ k}\Omega)^2 + (2\pi \cdot 4 \text{ MHz} \cdot 4.7 \text{ }\mu\text{H} - \frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}})^2}}$   
 Back to the first formula:  $R \cdot I = X_C \cdot I$   
 $R \cdot I = X_C \cdot I$   
 $R \cdot I = X_C \cdot I$

**Exercise E1 Resistance of a Wire by Resistivity**  
**(written test, approx. 6 % of a 60-minute written test, WS2022)**

2. For a heating element, it is required to heat the water in a tank with a volume of  $V = 180 \text{ l}$  by electric power dissipation (= heat flow) of  $P = 40 \text{ W}$ . Calculate the current  $I$  needed to operate the heating element.  
 The Nichrome wire has a resistivity of  $\rho = 1.10 \cdot 10^{-6} \text{ }\Omega \cdot \text{m}$ .  
 The heating element is  $l = 3 \text{ m}$  long and has a diameter of  $d = 3.57 \text{ mm}$ .

Solution

$$P = U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}}$$

$$R = \rho \cdot \frac{l}{A} = \rho \cdot \frac{l}{\pi \cdot (\frac{d}{2})^2}$$

$$I = \sqrt{\frac{P}{\rho \cdot \frac{l}{\pi \cdot (\frac{d}{2})^2}}} = \sqrt{\frac{P \cdot \pi \cdot (\frac{d}{2})^2}{\rho \cdot l}}$$

$$I = \sqrt{\frac{40 \text{ W} \cdot \pi \cdot (\frac{3.57 \text{ mm}}{2})^2}{1.10 \cdot 10^{-6} \text{ }\Omega \cdot \text{m} \cdot 3 \text{ m}}}$$

$$\sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \cdot \Omega}} \quad \text{align*}$$

$$\begin{aligned} R &= \rho \cdot l \cdot \frac{1}{A} \quad \& \quad | \quad \text{with } A = r^2 \cdot \pi = \\ &= \frac{1}{4} d^2 \cdot \pi \quad \& \quad R = \rho \cdot l \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ &= 1.10 \cdot 10^{-6} \cdot \Omega \cdot \text{m} \cdot \frac{4 \cdot 3 \cdot \text{m}}{(3.57 \cdot 10^{-3} \cdot \text{m})^2 \cdot \pi} \quad \& \quad \end{aligned}$$


**Exercise E4 Charging Capacitors**  
 (written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (with the light bulb) also consists of a DC voltage source  $U = 12 \text{ V}$ , a resistor  $R_1 = 20 \text{ }\Omega$ , a capacitor  $C = 100 \text{ }\mu\text{F}$ , and a light bulb  $R_B = 5 \text{ }\Omega$ . The switch  $S_1$  is closed, the voltage across the capacitor is again  $0 \text{ V}$  at the moment  $t_0 = 0 \text{ s}$  when the switch  $S_2$  is closed. Calculate the voltage  $u_c(t_2)$  across the capacitor at  $t_2 = 1 \text{ ms}$  after closing the switch.

**Solution:** To solve this, first create an equivalent linear voltage source from  $U$ ,  $R_1$ , and  $R_B$ .

$$\begin{aligned} \Delta U &= U \cdot \frac{R_B}{R_1 + R_B} = 12 \text{ V} \cdot \frac{5 \text{ }\Omega}{20 \text{ }\Omega + 5 \text{ }\Omega} = 2 \text{ V} \end{aligned}$$


On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting  $R_B$ .



The circuit contains a voltage source  $U = 12 \text{ V}$ , a switch  $S_1$ , a resistor of  $R_1 = 20 \text{ }\Omega$  and a capacitor of  $C = 100 \text{ }\mu\text{F}$ . The switch  $S_2$  to an additional consumer  $R_B$  will be considered to be open for the first tasks. At the moment  $t_0 = 0 \text{ s}$  the switch  $S_1$  is closed, the voltage across the capacitor is  $u_c(t_0) = 0 \text{ V}$ .

.. First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time  $t_1$  when  $u_c(t_1) = 0.5 \cdot U$ .

Solution



An equivalent linear voltage source can be given with  $U_s$ ,  $R_1$ , and  $R_B$  as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is:  $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$  The internal resistance is given by substituting the ideal voltage source with its resistance ( $R = 0 \Omega$ , short-circuit).

$$R_i = R_1 \parallel R_B = 10 \Omega$$

$$u_c(t) = U_s \cdot (1 - e^{-t/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-t/(10 \Omega \cdot 100 \mu F)})$$

The following formula describes the time course of  $u_c(t)$  which has to be  $u_c(t_1) = 0.5 \cdot U$ : 
$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to  $(1 - e^{-t/\tau}) = 0.5 \implies e^{-t/\tau} = 0.5 \implies t/\tau = \ln(0.5) \implies t = \tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$



**Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)**

The following shall be solved at 0.1 A.  $R_1 = 10 \Omega$ ,  $R_2 = R_3 = 15 \Omega$ ,  $R_4 = 20 \Omega$  and the voltage  $U = 10 V$  is given.  $R_B$ .

Solution

$$R_{\text{eq}} = 132.8 \Omega$$

Now a wye-delta transformation is necessary.



Since  $R_2=R_3$  and based on the equations for the transformation, the transformed  $R_Y$  is given as:


$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \, \Omega)^2}{3 \cdot 100 \, \Omega} = \frac{1}{3} \cdot 100 \, \Omega = 33.33 \, \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \, \Omega + (33.33 \, \Omega + 400 \, \Omega) \parallel (33.33 \, \Omega + 100 \, \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance  $R_{\text{eq}}$  between  $A$  and  $B$ .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \sim \Omega + 200 \sim \Omega + 200 \sim \Omega) \parallel (100 \sim \Omega + 100 \sim \Omega) \parallel R_{\text{eq}} = \{500 \sim \Omega \parallel (200 \sim \Omega) \parallel R_{\text{eq}} = \{500 \sim \Omega \cdot 200 \sim \Omega \} \over {500 \sim \Omega + 200 \sim \Omega} \}$$

From: <https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: [https://mexle.te.hs-heilbronn.de/electrical\\_engineering\\_1/ws2022\\_exam?rev=1680124746](https://mexle.te.hs-heilbronn.de/electrical_engineering_1/ws2022_exam?rev=1680124746)

Last update: 2023/03/29 23:19

