

calc_decimal_example

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

$\$1.\!\!\!\!\!\quad$ Calculation example for decimal value

value		2	6	5	8	4	7
index	i	3	2	1	0	-1	-2
place value	B^i	10^3 \$1000	10^2 \$100	10^1 \$10	10^0 \$1	10^{-1} \$0.1	10^{-2} \$0.01
digit	z_i	2	6	5	8	4	7
calculation	$z_i \cdot B^i$	2000	600	50	8	0.4	0.07
Result	$\sum_i z_i \cdot B^i$	2658,47					

[illegible]

\$II.\quad\$ Betrachtung der Spannungsverstärkung

aus (0)	$\$color{blue}\{A_V\}=\frac{\$color{blue}\{U_A\}}{\$color{blue}\{U_E\}}\$$	$\$quad\$$
$\$quad\$$	$\$quad\$$	$\$quad\$$
$\$quad\$$	$\$A_V=\frac{\$color{blue}\{U_A\}}{\$color{blue}\{U_E\}}\$$	mit (4): $\$U_E=U_2+U_D\$$
$\$quad\$$	$\$quad\$$	$\$quad\$$
$\$quad\$$	$\$A_V=\frac{\$color{blue}\{U_A\}}{\$color{blue}\{U_2+U_D\}}\$$	$\$quad\$$
$\$quad\$$	$\$quad\$$	$\$quad\$$
$\$quad\$$	$\$A_V=\frac{\$color{blue}\{U_A\}}{\$color{blue}\{U_2\}+U_D\$}$	mit (10): $\$U_2=\frac{\$color{blue}\{R_2\}}{\$color{blue}\{R_1+R_2\}}\$$
$\$quad\$$	$\$quad\$$	$\$quad\$$
$\$quad\$$	$\$A_V=\frac{\$color{blue}\{U_A\}}{\$color{blue}\{U_A\}+\frac{\$color{blue}\{R_2\}}{\$color{blue}\{R_1+R_2\}}+U_D\$}$	$\$quad\$$
$\$quad\$$	$\$quad\$$	$\$quad\$$
$\$quad\$$	$\$A_V=\frac{\$color{blue}\{U_A\}}{\$color{blue}\{U_A\}+\frac{\$color{blue}\{R_2\}}{\$color{blue}\{R_1+R_2\}}+U_D\$}$	$\$quad\$$
$\$quad\$$	$\$quad\$$	$\$quad\$$
$\$quad\$$	$\$A_V=\frac{\$color{blue}\{U_A\}}{\$color{blue}\{U_A\}+\frac{\$color{blue}\{R_2\}}{\$color{blue}\{R_1+R_2\}}+\$color{blue}\{U_D\}}\$$	mit (1)
$\$quad\$$	$\$quad\$$	$\$quad\$$
$\$quad\$$	$\$A_V=\frac{\$color{blue}\{U_A\}}{\$color{blue}\{U_A\}+\frac{\$color{blue}\{R_2\}}{\$color{blue}\{R_1+R_2\}}+\$color{blue}\{U_D\}}\$$	$\$quad\$$
$\$quad\$$	$\$quad\$$	$\$quad\$$
$\$quad\$$	$\$A_V=\frac{\$color{blue}\{U_A\}}{\$color{blue}\{U_A\}+\frac{\$color{blue}\{R_2\}}{\$color{blue}\{R_1+R_2\}}+\frac{\$color{blue}\{U_A\}}{\$color{blue}\{A_D\}}\$}$	$\$quad\$$
$\$quad\$$	$\$quad\$$	$\$quad\$$
$\$quad\$$	$\$A_V=\frac{\$color{blue}\{U_A\}}{\$color{blue}\{U_A\}+\frac{\$color{blue}\{R_2\}}{\$color{blue}\{R_1+R_2\}}+\frac{\$color{blue}\{U_A\}}{\$color{blue}\{A_D\}}+\frac{\$color{blue}\{U_A\}}{\$color{blue}\{A_D\}}\$}$	Erweitern mit $\frac{\$color{blue}\{1\}}{\$color{blue}\{U_A\}}\$$
$\$quad\$$	$\$quad\$$	$\$quad\$$
$\$quad\$$	$\$A_V=\frac{\$color{blue}\{1\}}{\$color{blue}\{R_2\}+\frac{\$color{blue}\{R_2\}}{\$color{blue}\{R_1+R_2\}}+\frac{\$color{blue}\{1\}}{\$color{blue}\{A_D\}}\$}$	$\$quad\$$
$\$quad\$$	$\$quad\$$	$\$quad\$$
$\$quad\$$	$\$A_V=\frac{\$color{blue}\{1\}}{\$color{blue}\{R_2\}+\frac{\$color{blue}\{R_2\}}{\$color{blue}\{R_1+R_2\}}+\frac{\$color{blue}\{1\}}{\$color{blue}\{A_D\}}\$}$	mit $\frac{\$color{blue}\{1\}}{\$color{blue}\{A_D\}} \rightarrow 0\$$
$\$quad\$$	$\$quad\$$	$\$quad\$$
$\$quad\$$	$\$A_V=\frac{\$color{blue}\{1\}}{\$color{blue}\{R_2\}+\frac{\$color{blue}\{R_2\}}{\$color{blue}\{R_1+R_2\}}\$}$	Bruch umformen
$\$quad\$$	$\$quad\$$	$\$quad\$$
$\$quad\$$	$\$A_V=\frac{\$color{blue}\{R_1+R_2\}}{\$color{blue}\{R_2\}}\$$	$\$quad\$$
$\$quad\$$	$\$quad\$$	$\$quad\$$

From:

<https://mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

[https://mexle.te.hs-heilbronn.de/introduction to digital systems/calc decimal example?rev=1631661940](https://mexle.te.hs-heilbronn.de/introduction%20to%20digital%20systems/calc%20decimal%20example?rev=1631661940)

Last update: **2021/09/15 01:25**

