

Inverting Operational Amplifier

Student Group

| First Name | Surname | Matrikel Nr. |
|------------|---------|--------------|
| | | |
| | | |
| | | |

Table of Contents

| | |
|--|---|
| Inverting Operational Amplifier | 2 |
| Gain of Op-Amp | 2 |
| Investigation of inverting input | 3 |

Inverting Operational Amplifier

Gain of Op-Amp

Build the following circuit in [figure 1](#) with the power supply and a multimeter.



Fig. 1: Inverting Op-Amp

$U_{DD} = 10\text{ V}$, $U_{SS} = -10\text{ V}$, $R_1 = 10\text{ k}\Omega$

Calculate the necessary value for R_2 , so that the Output U_{OUT} is $+5\text{ V}$. Use the supply voltage of the operational amplifier for U_{IN} .

$U_{IN} =$

$$R_2$$

Investigation of inverting input




Fig. 2: Inverting Op-Amp: Investigate currents of the inverting input

$U_{DD} = 10\text{V}$, $U_{SS} = -10\text{V}$, $R_1 = 10\text{k}\Omega$

Use the values from [figure 1](#) for U_{IN} , U_{OUT} , R_2 .

Complete the arrows in the schematic of the circuit.

Determine the currents I_1 and I_2 indirectly by measuring the voltage.

Calculate the sum of the currents at node N_{12} .

$$U_1$$

$$U_2$$

$$I_{\text{1}} \approx 0 \text{ A}$$

$$I_{\text{2}} \approx 0 \text{ A}$$

$$I_{\text{N12}} \approx 0 \text{ A}$$



Fig. 3: Inverting Op-Amp: Investigate the virtual GND of the inverting input

$$U_{\text{DD}} \approx 10 \text{ V}, U_{\text{SS}} \approx -10 \text{ V}, R_{\text{1}} \approx 10 \text{ k}\Omega$$

Use the values from figure 1 for $U_{\text{IN}}, U_{\text{OUT}}, R_{\text{2}}$.

Complete the arrows in the scematic of the circuit.

Take the values for $U_{\text{1}}, U_{\text{2}}$ from the mesurments figure 2 .

Calculate the sum of the voltages at node N_{12} and compare it to measurement. What are your results?

$$U_{\text{1}} \approx \text{...}$$

$$U_{\text{2}} \approx \text{...}$$

$$\text{Calculated } U_{\text{N12}} \approx \text{...}$$

$$\text{Measured } U_{\text{N12}} \approx \text{...}$$

- Virt masse messen
- r2 kurzschluss

From:

<https://mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

https://mexle.te.hs-heilbronn.de/lab05_en/inverting_op-amp_basics_amplification?rev=1775123557

Last update: **2026/04/02 11:52**

