

# Photodiode as current source

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Photo Diode as current source ..... 2

### Photo Diode as current source



Fig. 1: Inverting Op-Amp: Photo Diode BPW 34 S



Fig. 2: Inverting Op-Amp: Diagramms of BPW 34 S



Fig. 3: Inverting Op-Amp: Photo Diode as current source

$$U_{DD} \approx 10\text{ V}, \quad U_{SS} \approx -10\text{ V}$$

We assume a good illuminated room of 300 lx, illuminated by a white LED. White light is a mixture of many wavelengths across the visible spectrum, roughly 380 to 780 nm. For a typical white LED, the spectrum usually comes from a blue LED chip with a peak around 450 nm, plus a broader phosphor emission that spreads across green, yellow, and red wavelengths. For an easier calculation, we take a mean value of 500 nm which is close to the peak value of the blue LED (in reality a greenish light) and 300 lx for the illumination. In the diagram in figure 2 we see that the sensitivity of the photo diode at 500 nm ist only 30%. The maximim current (100%) at 300 lx is 30  $\mu\text{A}$ . Now we can calculate the current we expect from the diode at 300 lx:

$$I_1 = 30\ \mu\text{A} * 0.3$$

$$I_1 \approx 10\ \mu\text{A}$$

30% of 30  $\mu\text{A}$  is roughly 10  $\mu\text{A}$ .

Complete the arrows in the scematic of the circuit. Calculate  $R_2$  so that  $U_{OUT} = 5\text{ V}$  at 300 lx. Take a resistor from the E6 series that is as close as possible to the calculated value.

$$I_1 \approx$$

$$I_2 \approx$$

$$U_{OUT} \approx$$

$$U_2 \approx$$

$$R_2 \approx$$

What value would you expect for  $U_D$  and why?

$$U_D \approx$$

$\dots$

$\dots$

$\dots$

$\dots$

$\dots$

$\dots$

What value would you expect for  $U_{\text{D}}$  when it is not connected to the Op-Amp or any other electronic component (open-circuit voltage) at 300 lx?

$U_{\text{D}} \approx$

$\text{.....}$

$\text{.....}$

$\text{.....}$

$\text{.....}$

$\text{.....}$

From:  
<https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:  
[https://mexle.te.hs-heilbronn.de/lab05\\_en/inverting\\_op-amp\\_photo\\_diode\\_as\\_current\\_source?rev=1776676444](https://mexle.te.hs-heilbronn.de/lab05_en/inverting_op-amp_photo_diode_as_current_source?rev=1776676444)

Last update: 2026/04/20 11:14

