

Photodiode as current source

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Photodiode as current source 2

Photodiode as current source



Fig. 1: Inverting Op-Amp: Photodiode BPW 34 S



Fig. 2: Inverting Op-Amp: Diagramms of BPW 34 S




Fig. 3: Inverting Op-Amp: Photo Diode as current source

$$U_{DD} \approx 10\text{V}, U_{SS} \approx -10\text{V}$$

We assume a good illuminated room of 300 lx, illuminated by a white LED. White light is a mixture of many wavelengths across the visible spectrum, roughly 380 to 780 nm. For a typical white LED, the spectrum usually comes from a blue LED chip with a peak around 450 nm, plus a broader phosphor emission that spreads across green, yellow, and red wavelengths. For an easier calculation, we take a mean value of 500 nm which is close to the peak value of the blue LED (in reality a greenish light) and 300 lx for the illumination.

The graph in figure 2 shows that the photodiode sensitivity at 500 nm is only 30%. The maximum current (100%) at 300 lx is 30 μA .

We can now estimate the current we would expect from the photodiode at 300 lx:

$$I_1 = 30\ \mu\text{A} * 0.3 = 9\ \mu\text{A}$$

$$I_1 \approx 10\ \mu\text{A}$$

30% of 30 μA is roughly 10 μA .

We will assume a current of 10 μA at 300 lx for our calculations.

Complete the arrows in the schematic of the circuit in figure 3.

Calculate R_2 so that $U_{OUT} = 5\text{V}$ at 300 lx. Take a resistor from the E6 series that is as close as possible to the calculated value.

Also enter the values for I_1 , I_2 , U_2 and U_{OUT} .

$$I_1 = \text{ } \mu\text{A}$$

$$I_{R2} \approx$$

$$U_{R2} \approx$$

$$U_{OUT} \approx$$

$$R_{R2} \approx$$

What value would you expect for U_D and why?

$$U_D \approx$$

$$\{ \dots \}$$

$$\{ \dots \}$$

$$\{ \dots \}$$

$$\{ \dots \}$$

$$\{ \dots \}$$

$$\{ \dots \}$$

From:
<https://mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:
https://mexle.te.hs-heilbronn.de/lab05_en/inverting_op-amp_photo_diode_as_current_source?rev=1776696093

Last update: **2026/04/20 16:41**

